# Aggregate Facility Study SPP-2011-AGP1-AFS-10

1/18/2013

SPP Engineering, SPP Transmission Service Studies



# **Table of Contents**

Table of Contents	1
Executive Summary	2
Introduction	3
Financial Analysis	5
Third-Party Facilities	6
Study Methodology	7
Description	7
Model Development	7
Transmission Request Modeling	8
Transfer Analysis	8
Curtailment and Redispatch Evaluation	8
Study Results	9
Study Analysis Results	9
Example A:	10
Example B:	10
Example C:	11
Study Definitions	11
Conclusion	12
Appendix A	13
BASE CASE SETTINGS:	13
ACCC CASE SETTINGS.	12

# **Executive Summary**

Pursuant to Attachment Z1 of the Southwest Power Pool, Inc. (SPP) Open Access Transmission Tariff (OATT), 3358 MW of long-term transmission service requests have been studied in this Aggregate Facility Study (AFS). The principal objective of the AFS is to identify system problems and potential modifications necessary to facilitate these transfers while maintaining or improving system reliability, as well as summarizing the operating limits and determination of the financial characteristics associated with facility upgrades. A highly tangible benefit of studying transmission requests aggregately under the SPP OATT Attachment Z1 is the sharing of costs among Transmission Customers using the same facility. Facility upgrade costs are allocated on a prorated basis to all requests positively impacting any individual overloaded facility.

Attachment Z2 further provides for facility upgrade cost recovery by stating: "Transmission Customers paying Directly Assigned Upgrade Costs for Service Upgrades or that are in excess of the Safe Harbor Cost Limit for Network Upgrades associated with new or changed Designated Resources and Project Sponsors paying Directly Assigned Upgrade Costs for Sponsored Upgrades shall receive revenue credits in accordance with Attachment Z2. Generation Interconnection Customers paying for Network Upgrades shall receive credits for new transmission service using the facility as specified in Attachment Z1."

- The AFS determined that the total assigned facility upgrade Engineering and Construction (E&C) cost is \$5 Million. Additionally, \$0 dollars of assigned E&C cost for third party facility upgrades are assignable to the customer.
- Total upgrade levelized revenue requirements for all transmission requests after consideration of potential base plan funding is \$1 Million.

To accommodate the requested SPP Transmission Service, third-party facilities must be upgraded when the third-party transmission provider determines that they are constrained. Third-party facilities include both first-tier neighboring facilities outside SPP and Transmission Owner facilities within SPP that are not under the SPP OATT. In this AFS, third-party facilities were not identified. Total E&C cost estimates for required third-party facility upgrades are applicable.

SPP will tender a Letter of Intent on January 18, 2013. This will open a 15-day window for Customer response. To remain in the Aggregate Transmission Service Study (ATSS), SPP must receive from the Customer by February 2, 2013, an executed Letter of Intent. The Letter of Intent will list options the Customer must choose to clarify their commitment to remain in the ATSS. The only action required on OASIS is to withdraw the request or leave the request in study mode.

At the conclusion of the ATSS, Service Agreements for each request for service will be tendered identifying the terms and conditions of the confirmed service.

If Customers withdraw from the ATSS after posting of this AFS, the AFS will be re-performed to determine final cost allocation and Available Transmission Capability (ATC) in consideration of the

remaining ATSS participants. All allocated revenue requirements for facility upgrades are assigned to the Customer in the AFS data tables. Potential base plan funding allowable is contingent upon validation of designated resources meeting Attachment J, Section III B criteria.

## Introduction

Important milestones and dates in SPP's Aggregate Transmission Study process:

- In 2005, the Federal Energy Regulatory Commission (FERC) accepted SPP's proposed Aggregate Transmission Study procedures in Docket ER05-109.
- In 2008, in Docket ER08-1379-000 SPP filed with FERC to pair open seasons closing during January 2010 with an effective date of August 9, 2008.
- In January 2010, in Docket ER10-659-000 SPP filed with FERC to extend its current practice of pairing open seasons through January 31, 2011, with an effective date of January 28, 2010.
- In March 2010, in Docket ER10-659-000 FERC issued a letter order accepting SPP's proposal to continue to pair open seasons through January 31, 2011, effective January 28, 2010.
- The 2010-AG3 open season commenced June 1, 2010 and closed September 30, 2010.
- The 2011-AG1 open season commenced October 1, 2010 and closed January 31, 2011.
- All requests for long-term transmission service with a signed study agreement received before October 1, 2010 for 2010-AG3 and February 1, 2011 for 2011-AG1 have been included in the first paired Aggregate Transmission Service Study (ATSS) of 2011.

Approximately 3358 MW of long-term Transmission Service was studied in this Aggregate Facility Study (AFS), and over \$5 Million in transmission upgrades is proposed. The results of the AFS are detailed in Tables 1 through 6. Detailed results depict individual upgrade costs by study and potential base plan allowances determined by Attachments J and Z1. The OATT may be accessed at SPP's website by going to SPP.org>Org Groups>Governing Documents.

To understand the extent to which Base Plan Upgrades may be applied to both Point-to-Point (PTP) and Network Transmission Services, it is necessary to highlight the definition of Designated Resource. Per Section 1.9a of the SPP OATT, a Designated Resource is:

"[a]ny designated generation resource owned, purchased or leased by a Transmission Customer to serve load in the SPP Region. Designated Resources do not include any resource, or any portion thereof, that is committed for sale to third parties or otherwise cannot be called upon to meet the Transmission Customer's load on a non-interruptible basis."

Southwest Power Pool, Inc.

Network and PTP service has potential for base plan funding if the conditions for classifying upgrades associated with designated resources as Base Plan Upgrades as defined in Section III.B of Attachment J are met.

Pursuant to Attachment J, Section III B of the SPP OATT, the Transmission Customer must provide SPP information necessary to verify that the new or changed Designated Resource meets the following conditions:

- 1. Transmission Customer's commitment to the requested new or changed Designated Resource must have a duration of at least five years.
- 2. During the first year the Designated Resource is planned to be used by the Transmission Customer, the accredited capacity of the Transmission Customer's existing Designated Resources plus the lesser of:
  - a. The planned maximum net dependable capacity applicable to the Transmission Customer or
  - b. The requested capacity; shall not exceed 125% of the Transmission Customer's projected system peak responsibility determined pursuant to SPP Criteria 2.

According to Attachment Z1 Section VI.A, PTP customers pay the higher of the monthly transmission access charge (base rate) or the monthly revenue requirement associated with the assigned facility upgrades, including any prepayments for redispatch required during construction.

Network Integration Service Customers pay the total monthly transmission access charges and the monthly revenue requirement associated with the facility upgrades, including any prepayments for redispatch during construction.

Transmission Customers paying for a directly assigned Network Upgrade shall receive credits for new transmission service using the facility as specified in Attachment Z2.

Facilities identified as limiting the requested Transmission Service have been reviewed to determine the required in-service date of each Network Upgrade. The year that each Network Upgrade is required to accommodate a request is determined by interpolating between the applicable model years given the respective loading data. Both previously assigned facilities and the facilities assigned to this request for Transmission Service were evaluated.

In some instances, due to lead times for engineering and construction, Network Upgrades may not be available when required to accommodate a request for Transmission Service. When this occurs, the ATC with available Network Upgrades will be less than the capacity requested during either a portion of or all of the requested reservation period. As a result, the lowest seasonal allocated ATC within the requested reservation period will be offered to the Transmission Customer on an applicable annual basis as listed in Table 1. The ATC may be limited by transmission owner planned projects, expansion plan projects, or Customer assigned upgrades.

Some constraints identified in the AFS were not assigned to the Customer because SPP, the Transmission Provider, determined that upgrades are not required due to various reasons or the

Transmission Owner has construction plans pending for these upgrades. These facilities are listed by reservation in Table 3. This table also includes constrained facilities in the current planning horizon that limit the rollover rights of the Transmission Customer. Table 6 lists possible redispatch pairs to allow start of service prior to completion of assigned Network Upgrades. Table 7 (if applicable) lists deferment of expansion plan projects with different upgrades with the new required in service date as a result of this AFS.

# **Financial Analysis**

The AFS utilizes the allocated Customer's E&C cost in a present worth analysis to determine the monthly levelized revenue requirement of each facility upgrade over the term of the reservation. In some cases, Network Upgrades cannot be completed within the requested reservation period, thus deferred reservation periods will be utilized in the present worth analysis. If the Customer chose Option 2, Redispatch, in the Letter of Intent sent coincident with the initial AFS, the present worth analysis of revenue requirements will be based on the deferred term with redispatch in the subsequent AFS. The upgrade levelized revenue requirement includes interest, depreciation, and carrying costs.

Each request for Transmission Service is evaluated independently as the cost associated with each Network Upgrade is assigned to a request. When facilities are upgraded throughout the reservation period, the Transmission Customer shall 1) pay the total E&C costs and other annual operating costs associated with the new facilities, and 2) receive credits associated with the depreciated book value of removed usable facilities; salvage value of removed non-usable facilities; and the carrying charges, excluding depreciation, associated with all removed usable facilities based on their respective book values.

In the event that the engineering and construction of a previously assigned Network Upgrade may be accelerated, with no additional upgrades, to accommodate a new request for Transmission Service, the levelized present worth of only the incremental expenses though the reservation period of the new request, excluding depreciation, shall be assigned to the new request. These incremental expenses, excluding depreciation, include:

- 1. The levelized difference in present worth of the engineering and construction expenses given the change in date to complete construction to account for additional interest expense and reduced engineering and construction expense due to inflation,
- 2. The levelized present worth of all expediting fees, and
- 3. The levelized present worth of the incremental annual carrying charges, excluding depreciation and interest, during the new reservation period taking into account both:
  - a. The reservation in which the project was originally assigned, and
  - b. A reservation, if any, in which the project was previously accelerated.

In the case of a Base Plan Upgrade being displaced or deferred by an earlier in service date for a requested upgrade, achievable base plan avoided revenue requirements shall be determined per Attachment J, Section VII.B methodology. A deferred Base Plan Upgrade is defined as a different requested Network Upgrade needed at an earlier date that negates the need for the initial Base Plan Upgrade within the planning horizon. A displaced Base Plan Upgrade is defined as the same Network Upgrade being displaced by a requested upgrade needed at an earlier date.

A 40-year service life assumption is utilized for Base Plan funded projects, unless another assumption is provided by the Transmission Owner. A present worth analysis of revenue requirements on a common year basis between the Base Plan and Requested Upgrades was performed to determine avoided Base Plan revenue requirements due to the displacement or deferral of the Base Plan Upgrade by the Requested Upgrade. The difference in present worth between the Base Plan and Requested Upgrades is assigned to the transmission requests impacting this upgrade based on the displacement or deferral.

# Third-Party Facilities

For third-party facilities listed in Table 3 and Table 5, the Transmission Customer is responsible for funding the necessary upgrades of these facilities per Section 21.1 of the Transmission Provider's OATT. In this AFS, no third-party facilities were identified. The Transmission Provider will undertake reasonable efforts to assist the Transmission Customer in making arrangements for necessary engineering, permitting, and construction of the third-party facilities. Third-party facility upgrade E&C cost estimates are not utilized to determine the present worth value of levelized revenue requirements for SPP system Network Upgrades.

All modeled facilities within the Transmission Provider system were monitored during the development of this study, as well as certain facilities in first-tier neighboring systems. Third-party facilities must be upgraded when it is determined that they are overloaded while accommodating the requested Transmission Service. An agreement between the Customer and third party owner detailing the mitigation of the third party impact must be provided to the Transmission Provider prior to tendering of a Transmission Service Agreement. These facilities also include those owned by members of the Transmission Provider who have not placed their facilities under the Transmission Provider's OATT. Upgrades on the Southwest Power Administration network requires prepayment of the upgrade cost prior to construction of the upgrade.

Third-party facilities are evaluated for only those requests whose load sinks within the SPP footprint. The Customer must arrange for study of third party facilities for load that sinks outside the SPP footprint with the applicable Transmission Providers.

# Study Methodology

### **Description**

The facility study analysis was conducted to determine the steady-state impact of the requested service on the SPP and first tier non-SPP control area systems. The steady-state analysis was performed to ensure current SPP Criteria and NERC Reliability Standards requirements are fulfilled. SPP conforms to NERC Reliability Standards, which provide strict requirements related to voltage violations and thermal overloads during normal conditions and during a contingency. NERC Standards require all facilities to be within normal operating ratings for normal system conditions and within emergency ratings after a contingency.

Normal operating ratings and emergency operating ratings monitored are Rate A and B in the SPP Model Development Working Group (MDWG) models, respectively. The upper bound and lower bound of the normal voltage range monitored is 105% and 95%. The upper bound and lower bound of the emergency voltage range monitored is 105% and 90%. Transmission Owner voltage monitoring criteria is used if more restrictive. The SPS Tuco 230 kV bus voltage is monitored at 92.5% due to pre-determined system stability limitations. The WERE Wolf Creek 345 kV bus voltage is monitored at 103.5% and 98.5% due to transmission operating procedure.

The contingency set includes all SPP control area branches and ties 69 kV and above; first tier non-SPP control area branches and ties 115 kV and above; any defined contingencies for these control areas; and generation unit outages for the control areas with SPP reserve share program redispatch. The monitor elements include all SPP control area branches, ties, and buses 69 kV and above, and all first tier non-SPP control area branches and ties 115 kV and above. Voltage monitoring was performed for SPP control area buses 69 kV and above.

A 3 % transfer distribution factor (TDF) cutoff was applied to all SPP control area facilities. For first tier non-SPP control area facilities, a 3 % TDF cutoff was applied to AECI, AMRN (Ameren), and ENTR (Entergy) control areas. A 2 % TDF cutoff was applied to WAPA. For voltage monitoring, a 0.02 per unit change in voltage must occur due to the transfer or modeling upgrades to be considered a valid limit to the transfer

## **Model Development**

SPP used five seasonal models to study the aggregate transfers of 3358 MW over a variety of requested service periods. The following SPP Transmission Expansion Plan 2011 Build 2 Cases were used to study the impact of the requested service on the transmission system:

2013 Summer Peak (13SP)

2013/14 Winter Peak (13WP)

2017 Summer Peak (17SP)

2017/18 Winter Peak (17WP)

2022 Summer Peak (22SP)

The Summer Peak models apply to June through September and the Winter Peak models apply to December through March.

Southwest Power Pool, Inc.

The chosen base case models were modified to reflect the current modeling information. One group of requests was developed from the aggregate of 3358 MW to model the requested service. From the five seasonal models, two system scenarios were developed. Scenario 0 includes projected usage of transmission included in the SPP 2011 Series Cases. Scenario 5 includes transmission service not already included in the SPP 2011 Series Cases.

### **Transmission Request Modeling**

Network Integration Transmission Service requests are modeled as Generation to Load transfers in addition to Generation to Generation transfers. Network Integration Transmission Service requests are modeled as Generation to Load transfers in addition to Generation to Generation because the requested Network Integration Transmission Service is a request to serve network load with the new designated network resource, and the impacts on Transmission System are determined accordingly. Point-To-Point Transmission Service requests are modeled as Generation to Generation transfers. Generation to Generation transfers are accomplished by developing a post-transfer case for comparison by dispatching the request source and redispatching the request sink.

### **Transfer Analysis**

Using the selected cases both with and without the requested transfers modeled, the PSS/E Activity ACCC was run on the cases and compared to determine the facility overloads caused or impacted by the transfer. Transfer distribution factor cutoffs (SPP and 1<sup>st</sup>-Tier) and voltage threshold (0.02 change) were applied to determine the impacted facilities. The PSS/E options chosen to conduct the analysis can be found in Appendix A.

## Curtailment and Redispatch Evaluation

During any period in which SPP determines that a transmission constraint exists on and may impair Transmission System reliability, SPP will take whatever actions are reasonably necessary to maintain reliability. If SPP determines Transmission System reliability can be maintained by redispatching resources, it will evaluate the interim curtailment of existing confirmed service or interim redispatch of units to provide service prior to completion of any assigned Network Upgrades. Any redispatch may not unduly discriminate between the Transmission Owners' use of the Transmission System on behalf of their Native Load Customers and any Transmission Customer's use of the Transmission System to serve its designated load. Redispatch was evaluated to provide only interim service during the time frame prior to completion of any assigned Network Upgrades. Curtailment of existing confirmed service is evaluated to provide only interim service. Curtailment of existing confirmed service is only evaluated at the request of the transmission Customer.

SPP determined potential relief pairs to relieve the incremental MW impact on limiting facilities as identified in Table 6. Using the selected cases where the limiting facilities were identified, potential incremental and decremental units were identified by determining the generation amount available for increasing and decreasing from the units generation amount, maximum generation amount, and minimum generation amount. If the incremental or decremental amount was greater than 1 MW, the unit was considered as a potential incremental or decremental unit.

Southwest Power Pool, Inc.

Generation shift factors were calculated for the potential incremental and decremental units using Managing and Utilizing System Transmission (MUST). Relief pairs from the generation shift factors for the incremental and decremental units with a greater than 3% TDF on the limiting constraint were determined from the incremental units with the lowest generation shift factors and decremental units with highest generation shift factors. If the aggregate redispatch amount for the potential relief pair was determined to be three times greater than the lower of the increment or decrement, then the pair was determined not to be feasible and is not included. Transmission Customers can request SPP to provide additional relief pairs beyond those determined. The potential relief pairs were not evaluated to determine impacts on limiting facilities in the SPP and first tier systems. The SPP Reliability Coordinator would call upon the redispatch requirements before implementing NERC TLR Level 5a.

# **Study Results**

## **Study Analysis Results**

Tables 1 through 6 contain the AFS steady-state analysis results. Table 1 identifies the participating long-term Transmission Service requests included in the AFS. This table lists deferred start and stop dates both with and without redispatch (based on Customer selection of redispatch if available) and the minimum annual allocated ATC without upgrades and season of first impact.

Table 2 identifies total E&C cost allocated to each Transmission Customer, letter of credit requirements, third party E&C cost assignments, potential base plan E&C funding (lower of allocated E&C or Attachment J Section III B criteria), total revenue requirements for assigned upgrades without consideration of potential base plan funding, point-to-point base rate charge, total revenue requirements for assigned upgrades with consideration of potential base plan funding, and final total cost allocation to the Transmission Customer. In addition, Table 2 identifies SWPA upgrade costs which require prepayment in addition to other allocated costs.

Table 3 provides additional details for each request including all assigned facility upgrades required, allocated E&C costs, allocated revenue requirements for upgrades, upgrades not assigned to the Customer but required for service to be confirmed, credits to be paid for previously assigned AFS or Generation Interconnection Network Upgrades, and any required third party upgrades.

Table 4 lists all upgrade requirements with associated solutions needed to provide Transmission Service for the AFS, minimum ATC per upgrade with season of impact, earliest date upgrade is required (DUN), estimated date the upgrade will be completed, in service (EOC), and estimated E&C cost.

Table 5 lists identified third-party constrained facilities.

Table 6 identifies potential redispatch pairs available to relieve the aggregate impacts on identified constraints to prevent deferral of start of service.

Table 7 (if applicable) identifies deferred expansion plan projects that were replaced with requested upgrades at earlier dates.

The potential base plan funding allowable is contingent on meeting each of the conditions for classifying upgrades associated with designated resources as Base Plan Upgrades as defined in Section III.B of Attachment J. If the additional capacity of the new or changed Designated Resource exceeds the 125% resource to load forecast for the year of start of service, the requested resource is not eligible for base plan funding of required Network Upgrades and the full cost of the upgrades is assignable to the Customer.

If the request is for wind generation, the total requested capacity of wind generation plus existing wind generation capacity shall not exceed 20% of the customer's projected system peak responsibility in the first year the Designated Resource is planned to be used by the customer. If the five-year term and 125% resource to load criteria are met, (as well as the 20% wind resource to load criteria for wind generation requests) the requested capacity is multiplied by \$180,000 to determine the potential base plan funding allowable. The maximum potential base plan funding allowable may be less than the potential base plan funding allowable, due to the E&C cost allocated to the customer being lower than the potential amount allowable to the Customer. The Customer is responsible for any assigned upgrade costs in excess of potential base plan E&C funding allowable. Network Upgrades required for wind generation requests located in a zone other than the Customer POD shall be allocated as 67% base plan region-wide charge and 33% directly assigned to the Customer.

Regarding application of base plan funding for PTP requests, if PTP base rate exceeds upgrade revenue requirements without taking into effect the reduction of revenue requirements by potential base plan funding, then the base rate revenue pays back the Transmission Owner for upgrades and no base plan funding is applicable as the access charge must be paid as it is the higher of "OR" pricing.

However, if initially the upgrade revenue requirements exceed the PTP base rate, then potential base plan funding would be applicable. The test of the higher of "OR" pricing would then be made against the remaining assignable revenue requirements versus PTP base rate. Examples are as follows:

#### Example A:

E&C allocated for upgrades is \$74 million with revenue requirements of \$140 million and PTP base rate of \$101 million. Potential base plan funding is \$47 million, with the difference of \$27 million E&C assignable to the Customer. If the revenue requirements for the assignable portion is \$54 million and the PTP base rate is \$101 million, the Customer will pay the higher amount (so-called "or pricing") of \$101 million base rate of which \$54 million revenue requirements will be paid back to the Transmission Owners for the upgrades, and the remaining revenue requirements of \$86 million (\$140 million less \$54 million) will be paid by base plan funding.

#### **Example B:**

E&C allocated for upgrades is \$74 million with revenue requirements of \$140 million and PTP base rate of \$101 million. Potential base plan funding is \$10 million with the difference of \$64 million

Southwest Power Pool, Inc.

E&C assignable to the Customer. If the revenue requirements for this assignable portion is \$128 million and the PTP base rate is \$101 million, the Customer will pay the higher amount of \$128 million revenue requirements to be paid back to the Transmission Owners, and the remaining revenue requirements of \$12 million (\$140 million less \$128 million) will be paid by base plan funding.

#### Example C:

E&C allocated for upgrades is \$25 million with revenue requirements of \$50 million and PTP base rate of \$101 million. Potential base plan funding is \$10 million. Base plan funding is not applicable as the higher amount of PTP base rate of \$101 million must be paid and the \$50 million revenue requirements will be paid from this.

The 125% resource to load determination is performed on a per request basis and is not based on a total of Designated Resource requests per Customer. A footnote will provide the maximum resource designation allowable for base plan funding consideration per Customer basis per year.

Base plan funding verification requires that each Transmission Customer with potential for base plan funding provide SPP attestation statements verifying that the firm capacity of the requested Designated Resource is committed for a minimum five year duration.

#### **Study Definitions**

- The date upgrade needed date (DUN) is the earliest date the upgrade is required to alleviate a constraint considering all requests.
- End of construction (EOC) is the estimated date the upgrade will be completed and in service.
- Total engineering and construction cost (E&C) is the upgrade solution cost as determined by the Transmission Owner.
- The Transmission Customer's allocation of the E&C cost is based on the request (1) having an impact of at least 3% on the limiting element, and (2) having a positive impact on the upgraded facility.
- Minimum ATC is the portion of the requested capacity that can be accommodated without upgrading facilities.
- Annual ATC allocated to the Transmission Customer is determined by the least amount of allocated seasonal ATC within each year of a reservation period.

## Conclusion

The results of the AFS show that limiting constraints exist in many areas of the regional Transmission System. Due to these constraints, Transmission Service cannot be granted unless noted in Table 3.

The Transmission Provider will tender a Letter of Intent on January 18, 2013. This will open a 15-day window for Customer response. To remain in the Aggregate Transmission Service Study (ATSS), the Transmission Provider must receive from the Transmission Customer) by February 2, 2013, an executed Letter of Intent. The Letter of Intent will list options the Customer must choose to clarify their commitment to remain in the ATSS. The only action required on OASIS is to WITHDRAW the request or leave the request in STUDY mode.

The Transmission Provider must receive an unconditional and irrevocable letter of credit in the amount of the total allocated E&C costs assigned to the Customer. This letter of credit is not required for those facilities that are fully base plan funded. The amount of the letter of credit will be adjusted down on an annual basis to reflect cost recovery based on revenue allocation. The Transmission Provider will issue notifications to construct Network Upgrades to the constructing Transmission Owner after filing of necessary service agreements at FERC.

# Appendix A

#### PSS/E CHOICES IN RUNNING LOAD FLOW PROGRAM AND ACCC

#### **BASE CASE SETTINGS:**

Fixed slope decoupled Newton-Raphson solution Solutions:

(FDNS)

Stepping Tap adjustment:

Tie lines and loads Area Interchange Control: Apply immediately • Var limits:

Solution Options:

X Phase shift adjustment

Flat start

\_ Lock DC taps

Lock switched shunts

#### ACCC CASE SETTINGS:

AC contingency checking (ACCC) Solutions:

0.5 MW mismatch tolerance: Rate A • System intact rating: • Contingency case rating: Rate B • Percent of rating: 100 • Output code: **Summary** 

Min flow change in overload report: 3mw Excld cases w/ no overloads from report: YES NO Exclude interfaces from report: Perform voltage limit check: YES Elements in available capacity table: 60000 99999.0

Cutoff threshold for available capacity table:

0.02 Min. contng. Case Vltg chng for report: None

Sorted output:

Newton Solution: Tap adjustment: Stepping

Tie lines and loads (Disabled for generator Area interchange control:

outages)

Apply immediately Var limits:

X Phase shift adjustment Solution options:

Flat start

Lock DC taps

\_\_ Lock switched shunts

**Table 1** - Long-Term Transmission Service Requests Included in Aggregate Facility Study

Customer	Study Number	Reservation	POR	POD	Requested Amount	Requested Start Date	Requested Stop Date	Deferred Start Date without interim redispatch	Deferred Stop Date without interim redispatch	Start Date with interim redispatch	Stop Date with interim redispatch	Minimum Allocated ATC (MW) within reservation period	Season of Minimum Allocated ATC within reservation period
AECC	AG1-2011-032	75197033	OKGE	OKGE	238	7/1/2015	7/1/2020	7/1/2015	7/1/2020	7/1/2015	7/1/2020	238	22SP
AECC	AG1-2011-036	75197522	SPA	OKGE	89	7/1/2015	7/1/2020	7/1/2015	7/1/2020	7/1/2015	7/1/2020	89	17SP
AECC	AG1-2011-038	75197570	CSWS	OKGE	710	7/1/2015	7/1/2020	7/1/2015	7/1/2020	7/1/2015	7/1/2020	710	17SP
AECC	AG1-2011-039	75197442	CSWS	CSWS	170	6/1/2015	6/1/2020	6/1/2015	6/1/2020	6/1/2015	6/1/2020	170	17SP
AECC	AG1-2011-040	75197472	CSWS	OKGE	170	7/1/2015	6/1/2020	7/1/2015	6/1/2020	7/1/2015	6/1/2020	170	17SP
AECC	AG1-2011-041	75197551	EES	OKGE	320	7/1/2015	7/1/2020	7/1/2015	7/1/2020	7/1/2015	7/1/2020	320	17SP
BPAE	AG1-2011-018	75181762	WR	AECI	50	11/1/2012	11/1/2017	6/1/2016	6/1/2021	6/1/2013	6/1/2018	0	13SP
BPAE	AG1-2011-019	75181747	WR	AECI	150	11/1/2012	11/1/2017	6/1/2016	6/1/2021	6/1/2013	6/1/2018	0	13SP
CRGL	AG1-2011-081	75199815	NPPD	EES	200	12/1/2012	12/1/2032	6/1/2013	6/1/2033	6/1/2013	6/1/2033	200	13SP
HZN	AG1-2011-055	75181743	WFEC	EES	100	1/1/2012	1/1/2017	6/1/2013	6/1/2018	Note 4	Note 4	100	13SP
KCPS	AG1-2011-011	75181547	NPPD	KCPL	20	1/1/2014	1/1/2024	1/1/2014	1/1/2024	1/1/2014	1/1/2024	0	13WP
KCPS	AG1-2011-012	75181564	NPPD	KCPL	20	1/1/2014	1/1/2024	1/1/2014	1/1/2024	1/1/2014	1/1/2024	0	13WP
KCPS	AG1-2011-013	75181568	NPPD	KCPL	22	1/1/2014	1/1/2024	1/1/2014	1/1/2024	1/1/2014	1/1/2024	0	13WP
KCPS	AG1-2011-057	75199886	SECI	KCPL	50	8/1/2011	9/1/2013	6/1/2013	9/1/2013	4/1/2012	9/1/2013	43	13WP
KCPS	AG1-2011-061	75199893	SECI	KCPL	50	8/1/2011	9/1/2013	6/1/2013	9/1/2013	4/1/2012	9/1/2013	43	13WP
KMEA	AG1-2011-094	75200249	SPA	SECI	1	11/1/2013	12/31/2018	11/1/2013	12/31/2018	11/1/2013	12/31/2018	0	22SP
KMEA	AG1-2011-095	75199561	OPPD	WR	6	2/1/2012	2/1/2017	6/1/2013	6/1/2018	6/1/2013	6/1/2018	6	13SP
KMEA	AG1-2011-096	75200582	SECI	SECI	23	1/1/2012	6/1/2026	1/1/2015	6/1/2029	6/1/2013	11/1/2027	0	13WP
LESM	AG1-2011-006	75134451	NPPD	LES	10	10/1/2012	10/1/2017	6/1/2013	6/1/2018	6/1/2013	6/1/2018	10	13SP
MIDW	AG1-2011-084	75200166	WR	WR	15	6/1/2012	6/1/2017	6/1/2016	6/1/2021	6/1/2013	6/1/2018	6	13SP
MIDW	AG1-2011-085	75200168	WR	WR	5	6/1/2012	6/1/2017	6/1/2016	6/1/2021	6/1/2013	6/1/2018	2	22SP
MIDW	AG1-2011-086	75200171	WR	WR	5	6/1/2012	6/1/2017	6/1/2016	6/1/2021	6/1/2013	6/1/2018	2	13SP
MIDW	AG1-2011-087	75200180	WR	WR	5	6/1/2013	6/1/2018	6/1/2016	6/1/2021	6/1/2013	6/1/2018	2	22SP
MIDW	AG1-2011-088	75200183	WR	WR	5	6/1/2013	6/1/2018	6/1/2016	6/1/2021	6/1/2013	6/1/2018	2	22SP
NPPM	AG1-2011-066	75200206	NPPD	NPPD	1	12/1/2012	12/1/2017	6/1/2013	6/1/2018	6/1/2013	6/1/2018	1	13SP
OMPA	AG1-2011-049	75180762	CSWS	CSWS	50	6/1/2014	9/30/2018	6/1/2014	9/30/2018	6/1/2014	9/30/2018	50	17SP
OMPA	AG1-2011-050	75196276	CSWS	OKGE	3	3/1/2012	12/31/2027	6/1/2013	4/1/2029	6/1/2013	4/1/2029	0	13SP
OPPM	AG1-2011-026	75180047	NPPD	OPPD	18	12/1/2012	12/1/2017	6/1/2013	6/1/2018	Note 4	Note 4	0	13WP
SECI	AG1-2011-108	75173900	SECI	SECI	80	7/1/2012	7/1/2032	6/1/2016	6/1/2036	6/1/2013	6/1/2033	0	13WP
SPSM	AG1-2011-064	75197996	SPS	SPS	42	6/1/2012	6/1/2045	1/1/2015	1/1/2048	9/1/2012	9/1/2045	0	13WP
SPSM	AG1-2011-065	75197998	SPS	SPS	29	6/1/2012	6/1/2032	1/1/2015	1/1/2035	9/1/2012	9/1/2032	0	22SP
TNSK	AG1-2011-029	75108845	KCPL	ERCOTE	44	8/1/2011	6/1/2014	6/1/2013	6/1/2014	6/1/2013	6/1/2014	0	13WP
TNSK	AG1-2011-030	75108838	KCPL	ERCOTE	6	8/1/2011	6/1/2014	6/1/2013	6/1/2014	6/1/2013	6/1/2014	0	13WP
WFEC	AG1-2011-097	75179329	CSWS	WFEC	150	1/1/2012	1/1/2037	1/1/2015	1/1/2040	6/1/2013	6/1/2038	0	13WP

 Table 1 - Long-Term Transmission Service Requests Included in Aggregate Facility Study

Customer	Study Number	Reservation	POR	POD	Requested Amount	Requested Start Date	Requested Stop Date	Deferred Start Date without interim redispatch	Deferred Stop Date without interim redispatch	Start Date with interim redispatch	Stop Date with interim redispatch	Allocated ATC (MW) within	Season of Minimum Allocated ATC within reservation period
WRGS	AG1-2011-002	74977737	OKGE	WR	300	1/1/2016	6/1/2027	1/1/2016	6/1/2027	Note 4	Note 4	300	17SP
WRGS	AG1-2011-003	75021167	WR	WR	201	10/1/2012	1/1/2032	12/1/2014	3/1/2034	6/1/2013	9/1/2032	109	13WP

Note 1: Start and Stop Dates with interim redispatch are determined based on customers choosing option to pursue redispatch to start service at Requested Start and Stop Dates or earliest date possible.

Note 2: Start dates with and without redispatch are based on the assumed completion dates of previous Aggregate Transmission Service Studies currently being conducted. Actual start dates may differ from the potential start dates upon completion of the previous studies.

Note 3: Request is unable to be deferred due to fixed stop dates.

Note 4: Transmission customer did not select "remain in the study using interim redispatch" option.

**Table 2** - Total Revenue Requirements Associated with Long-Term Transmission Service Requests

Customer	Study Number	Reservation	Engineering and Construction Cost of Upgrades Allocated to Customer for Revenue Requirements	<sup>1</sup> Letter of Credit Amount Required	<sup>2</sup> Potential Base Plan Engineering and Construction Funding Allowable	Notes	<sup>4</sup> Additional Engineering and Construction Cost for 3rd Party Upgrades	<sup>3 S</sup> Total Revenue Requirements for Assigned Upgrades Over Term of Reservation WITH Potential Base Plan Funding Allocation	Point-to-Point Base Rate Over Reservation Period	<sup>4</sup> Total Cost of Reservation Assignable to Customer Contingent Upon Base Plan Funding
AECC	AG1-2011-032	75197033	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
AECC	AG1-2011-036	75197522	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
AECC	AG1-2011-038	75197570	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
AECC	AG1-2011-039	75197442	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
AECC	AG1-2011-040	75197472	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
AECC	AG1-2011-041	75197551	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
BPAE	AG1-2011-018	75181762	\$ 110,183	\$ 110,183	\$ -		\$ -	\$ 149,552	\$ 2,634,000	\$ 2,634,000
BPAE	AG1-2011-019	75181747	\$ 330,550	\$ 330,550	\$ -		\$ -	\$ 448,659	\$ 7,902,000	\$ 7,902,000
CRGL	AG1-2011-081	75199815	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 57,049,440	\$ 57,049,440
HZN	AG1-2011-055	75181743	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 7,131,180	\$ 7,131,180
KCPS	AG1-2011-011	75181547	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
KCPS	AG1-2011-012	75181564	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
KCPS	AG1-2011-013	75181568	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
KCPS	AG1-2011-057	75199886	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 746,300	\$ 746,300
KCPS	AG1-2011-061	75199893	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 746,300	\$ 746,300
KMEA	AG1-2011-094	75200249	\$ 4,669	\$ -	\$ 4,669		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
KMEA	AG1-2011-095	75199561	\$ -	\$ -	\$ -	6	\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
KMEA	AG1-2011-096	75200582	\$ 51,632	\$ -	\$ 51,632		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
LESM	AG1-2011-006	75134451	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
MIDW	AG1-2011-084	75200166	\$ 1,698,453	\$ -	\$ 1,698,453		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
MIDW	AG1-2011-085	75200168	\$ 566,151	\$ -	\$ 566,151		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
MIDW	AG1-2011-086	75200171	\$ 566,151	\$ -	\$ 566,151		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
MIDW	AG1-2011-087	75200180	\$ 566,151	\$ -	\$ 566,151		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
MIDW	AG1-2011-088	75200183	\$ 566,151	\$ -	\$ 566,151		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
NPPM	AG1-2011-066	75200206	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 110,239	\$ 110,239
OMPA	AG1-2011-049	75180762	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
OMPA	AG1-2011-050	75196276	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
OPPM	AG1-2011-026	75180047	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
SECI	AG1-2011-108	75173900	\$ 714,647	\$ 235,834	\$ 478,813		\$ -	\$ 566,121	\$ -	\$ 566,121
SPSM	AG1-2011-064	75197996	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
SPSM	AG1-2011-065	75197998	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
TNSK	AG1-2011-029	75108845	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 832,519	\$ 832,519
TNSK	AG1-2011-030	75108838	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 113,525	\$ 113,525
WFEC	AG1-2011-097	75179329	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges

Table 2 - Total Revenue Requirements Associated with Long-Term Transmission Service Requests

Customer	Study Number	Reservation	Engineering and Construction Cost of Upgrades Allocated to Customer for Revenue Requirements	<sup>1</sup> Letter of Credit Amount Required	<sup>2</sup> Potential Base Plan Engineering and Construction Funding Allowable	Notes	<sup>4</sup> Additional Engineering and Construction Cost for 3rd Party Upgrades	Torm of Recorvation	Point-to-Point Base Rate Over Reservation Period	<sup>4</sup> Total Cost of Reservation Assignable to Customer Contingent Upon Base Plan Funding
WRGS	AG1-2011-002	74977737	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
WRGS	AG1-2011-003	75021167	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges
Grand Total			\$ 5,174,738		\$ 4,446,539			\$ 1,269,116		

Note 1: Letter of Credit required for financial security for transmission owner for network upgrades is determined by allocated engineering and construction costs less engineering and construction costs for upgrades when network customer is the transmission owner less the E & C allocation of expedited projects. Letter of Credit is required for upgrades assigned to PTP requests. The amount of the letter of credit will be adjusted down on an annual basis to reflect cost recovery based on revenue allocation. This letter of credit is not required for those facilities that are fully base plan funded. The Letter Of Credit Amount listed is based on meeting OATT Attachment J requirements for base plan funding.

Note 2: If potential base plan funding is applicable, this value is the lesser of the Engineering and Construction costs of assignable upgrades or the value of base plan funding is contingent upon verification of customer agreements meeting Attachment J, Section II B criteria. Not applicable if Point-to-Point base rate exceeds revenue requirements.

Note 3: Revenue Requirements (RR) are based upon deferred end dates if applicable. Deferred dates are based upon customer's choice to pursue redispatch. Achievable Base Plan Avoided RR in the case of a Base Plan upgrade being displaced or deferred by an earlier in service date for a Requested Upgrade shall be determined per Attachment J. Section VII.C methodology. Assumption of a 40 year service life is utilized for Base Plan funded projects. A present worth analysis of RR on a common year basis between the Base Plan and Requested Upgrades was performed to determine avoided Base Plan RR due to the displacement or deferral of the Base Plan upgrade by the Requested Upgrade. The incremental increase in present worth of a Requested Upgrade on a common year basis as a Base Plan upgrade is assigned to the transmission requests impacting the upgrade based on the displacement or deferral. If the displacement analysis results in lower RR due to the shorter amortization period of the requested upgrade when compared to a base plan amortization period, then no direct assignment of the upgrade cost is made due to the displacement to an earlier Note 4: For Point-to-Point requests, total cost is based on the higher of the base rate or assigned upgrade revenue requirements. For Network requests, the total cost is based on the assigned upgrade revenue requirements. For Network requests, the total cost is based on the assigned upgrade revenue requirements. For Network requests, the total cost is based on the assigned upgrade revenue requirements. For Network requests, the total cost is based on the assigned upgrade revenue requirements. This includes prepayments required for any SWPA upgrades. Revenue requirements for 3rd Party facilities are not calculated. Total cost to customer is based on assumption of Revenue Requirements with confirmation of base plan funding. Customer is responsible for negotiating redispatch costs if applicable. Customer is also responsible to pay credits for previously assigned upgrades that are impacte

Note 5: RR with base plan funding may increase or decrease even if no base plan funding is applicable to a particular request if another request that shares the upgrade is now full base plan funded resulting in a different amortization period for the upgrade and thus different RR.

Note 6: The estimated engineering and construction cost for the Pawnee to Larned 115 kV line has a 2009 year effective date. This estimate will be updated with a 2012 year effective date.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AECC	75197033	OKGE	OKGE	238	7/1/2015	7/1/2020			\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue	
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements	
75197033	None					\$ -	\$ -	\$	-
					Total	\$ -	\$ -	\$	-

 $<sup>\</sup>hbox{*Credits may be required for applicable generation interconnection network upgrades}.$ 

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AECC	75197522	SPA	OKGE	89	7/1/2015	7/1/2020			\$ -	\$ -	\$ -	\$ -
		•	•	•	•	•	•	•	\$ -	\$ -	\$ -	Ś -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75197522	None					\$ -	\$ -	\$
•					Total	\$ -	\$ -	Ś

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75197522	BEELINE - EXPLORER GLENPOOL 138KV CKT 1	6/1/2009	6/1/2009		
	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 AEPW	6/1/2009	6/1/2009		
	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 OKGE	6/1/2009	6/1/2009		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	KNOBHILL (KNOBHIL4) 138/69/13.2KV TRANSFORMER CKT 1	6/1/2006	6/1/2008		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	MCNAB REC - TURK 115KV CKT 1	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - IODINE 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AECC	75197570	CSWS	OKGE	710	7/1/2015	7/1/2020			\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75197570	None					\$ -	\$ -	\$ -
•					Total	\$ -	Ś -	\$ -

Reservation	Upgrade Name	DUN		Earliest Start Date	Redispatch Available
	ALBION - PETERSBURG 115KV CKT 1	1/1/2013		Date	Available
	ALEXANDER - PRATT 115KV CKT 1	12/1/2013			
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009			
	ALUMAX TAP - BANN 138KV CKT 1	6/1/2008	., ,		
	BEELINE - EXPLORER GLENPOOL 138KV CKT 1	6/1/2009			
	CANTON - TALOGA 69KV CKT 1	6/1/2011			
	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	6/1/2015			
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011			
	DEARING 138KV Capacitor	6/1/2012			
	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 AEPW	6/1/2009			
	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 OKGE	6/1/2009			
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009			
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009			
	FT RANDAL - MADISONCO 230.00 230KV CKT 1	10/1/2013	11/1/2014		
	G03-05T 138.00 - PARADISE 138KV CKT 1	6/1/2010			
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	7/1/2012	7/1/2012		
	KELLY - MADISONCO 230.00 230KV CKT 1	10/1/2013	11/1/2014		
	KNOBHILL (KNOBHIL4) 138/69/13.2KV TRANSFORMER CKT 1	6/1/2006	6/1/2008		
	MCNAB REC - TURK 115KV CKT 1	7/1/2012	7/1/2012		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	NELIGH - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	OKAY - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	SE TEXARKANA - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	SUB 110 - ORONOGO JCT SUB 167 - RIVERTON 161KV CKT 1	6/1/2011	6/1/2011		
	SUGAR HILL - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	TALOGA (TALOGA) 138/69/13.8KV TRANSFORMER CKT 1	10/1/2010			
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
W	WOODWARD - IODINE 138KV CKT 1	1/1/2010			
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010			
	WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010			
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010			1

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AECC	75197442	CSWS	CSWS	170	6/1/2015	6/1/2020			\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75197442	None					\$ -	\$ -	\$ -
•					Total	\$ -	Ś -	\$ -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75197442	ASHDOWN REC (MILLWOOD) - OKAY 138KV CKT 1	7/1/2012	7/1/2012		
	ASHDOWN REC (MILLWOOD) - PATTERSON 138KV CKT 1	7/1/2012	7/1/2012		
	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	MCNAB REC - TURK 115KV CKT 1	7/1/2012	7/1/2012		
	OKAY - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	SE TEXARKANA - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	SUGAR HILL - TURK 138KV CKT 1	7/1/2012	7/1/2012		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AECC	75197472	CSWS	OKGE	170	7/1/2015	6/1/2020			\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75197472	None					\$ -	\$ -	\$
•					Total	\$ -	\$ -	Ś

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75197472	ALUMAX TAP - BANN 138KV CKT 1	6/1/2008	6/1/2008		
	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	BEELINE - EXPLORER GLENPOOL 138KV CKT 1	6/1/2009	6/1/2009		
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 AEPW	6/1/2009	6/1/2009		
	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 OKGE	6/1/2009	6/1/2009		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	KNOBHILL (KNOBHIL4) 138/69/13.2KV TRANSFORMER CKT 1	6/1/2006	6/1/2008		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - IODINE 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AECC	75197551	EES	OKGE	320		7/1/2020			\$ -	\$ -	\$ -	\$ -
		•	•	•	•	•	•	•	\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75197551	None					\$ -	\$ -	\$ -
•					Total	\$ -	Ś -	\$ -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN		Date	Available
75197551	ALEXANDER - PRATT 115KV CKT 1	12/1/2009			
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	ALUMAX TAP - BANN 138KV CKT 1	6/1/2008	6/1/2008		
	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012			
	BEELINE - EXPLORER GLENPOOL 138KV CKT 1	6/1/2009			
	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	6/1/2015	6/1/2015		
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 AEPW	6/1/2009	6/1/2009		
	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 OKGE	6/1/2009	6/1/2009		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FT RANDAL - MADISONCO 230.00 230KV CKT 1	10/1/2013	11/1/2014		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	KELLY - MADISONCO 230.00 230KV CKT 1	10/1/2013	11/1/2014		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	MCNAB REC - TURK 115KV CKT 1	7/1/2012	7/1/2012		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	SUB 110 - ORONOGO JCT SUB 167 - RIVERTON 161KV CKT 1	6/1/2011	6/1/2011		
	SUGAR HILL - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - IODINE 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
BPAE	75181762	WR	AECI	50	11/1/2012	11/1/2017	6/1/201	6 6/1/2021	1 \$ -	\$ 2,634,000	\$ 110,183	\$ 149,552
									\$ -	\$ 2,634,000	\$ 110,183	\$ 149,552

				Earliest Start	Redispatch	Allocate	d E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		Total E & C Cost	Requirements
75181762	MIDWAY - ST JOE 161KV CKT 1 Reactor	6/1/2014	6/1/2015		Yes	\$	110,183	\$ 440,733	\$ 149,552
					Total	Ś	110.183	\$ 440,733	\$ 149,553

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181762	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		Yes

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181762	Multi - Centerton - Osage Creek 345 kV	6/1/2013	6/1/2016		Yes
	Multi - Flint Creek – Centerton 345 kV and Centerton- East Centerton 161 kV	6/1/2013	6/1/2014		Yes

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
7518176	2 HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
BPAE	75181747	WR	AECI	150	11/1/2012	11/1/2017	6/1/2016	6/1/2021	\$ -	\$ 7,902,000	\$ 330,550	\$ 448,659
		•	•	•	•	•	•		\$ -	\$ 7,902,000	\$ 330,550	\$ 448,659

				Earliest Start	Redispatch	Allocat	ed E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		Total E & C Cost	Requirements
75181747	MIDWAY - ST JOE 161KV CKT 1 Reactor	6/1/2014	6/1/2015		Yes	\$	330,550	\$ 440,733	\$ 448,659
,					Total	Ś	330.550	\$ 440,733	\$ 448,659

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181747	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		Yes

 $Reliability \ Projects - The \ requested \ service \ is \ contingent \ upon \ completion \ of \ the \ following \ upgrades. \ Cost \ is \ not \ assignable \ to \ the \ transmission \ customer.$ 

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181747	Multi - Centerton - Osage Creek 345 kV	6/1/2013	6/1/2016		Yes
	Multi - Flint Creek - Centerton 345 kV and Centerton- East Centerton 161 kV	6/1/2013	6/1/2014		Yes

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181747	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
CRGL	75199815	NPPD	EES	200	12/1/2012	12/1/2032	6/1/2013	6/1/2033	\$ -	\$ 57,049,440	\$ -	\$ -
				•	•		•	•	\$ -	\$ 57,049,440	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75199815	None					\$ -	\$ -	\$
		Total	\$ -	Ś -	Ś			

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75199815	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

Customer Study Number HZN AG1-2011-055

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
HZN	75181743	WFEC	EES	100	1/1/2012	1/1/2017	6/1/2013	6/1/2018	\$ -	\$ 7,131,180	\$ -	\$ -
		•	•	•	•	•		•	\$ -	\$ 7.131.180	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75181743	None					\$ -	\$ -	\$
					Total	\$ -	Ś -	Ś

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181743	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	MCNAB REC - TURK 115KV CKT 1	7/1/2012	7/1/2012		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KCPS	75181547	NPPD	KCPL	20	1/1/2014	1/1/2024			\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75181547	None					\$ -	\$ -	\$ -
•					Total	\$ -	Ś -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181547	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	10/1/2013	1/1/2015		
	Line - Thistle - Woodward 345 kV dbl Ckt PW	10/1/2013	1/1/2015		
	Line - Tuco - Woodward 345 kV line OKGE	10/1/2013	6/1/2014		
	Line - Tuco - Woodward 345 kV line SPS	10/1/2013	6/1/2014		

 $Reliability \ Projects - The \ requested \ service \ is \ contingent \ upon \ completion \ of \ the \ following \ upgrades. \ Cost \ is \ not \ assignable \ to \ the \ transmission \ customer.$ 

				Earliest Start	Redispatch	ı
Reservation	Upgrade Name	DUN	EOC	Date	Available	ı
75181547	MOUNDRIDGE 138/115KV TRANSFORMER CKT 2	10/1/2013	12/1/2014			ı

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181547	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KCPS	75181564	NPPD	KCPL	20	1/1/2014	1/1/2024			\$ -	\$ -	\$ -	\$ -
			•	•	•	•	•		\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue	٦
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements	
75181564	None					\$ -	\$ -	\$	-]
•					Total	\$ -	\$ -	\$	-

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181564	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	10/1/2013	1/1/2015		
	Line - Thistle - Woodward 345 kV dbl Ckt PW	10/1/2013	1/1/2015		
	Line - Tuco - Woodward 345 kV line OKGE	10/1/2013	6/1/2014		
	Line - Tuco - Woodward 345 kV line SPS	10/1/2013	6/1/2014		

 $Reliability \ Projects - The \ requested \ service \ is \ contingent \ upon \ completion \ of \ the \ following \ upgrades. \ Cost \ is \ not \ assignable \ to \ the \ transmission \ customer.$ 

				Earliest Start	Redispatch	ı
Reservation	Upgrade Name	DUN	EOC	Date	Available	ı
75181564	MOUNDRIDGE 138/115KV TRANSFORMER CKT 2	10/1/2013	12/1/2014			ı

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181564	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KCPS	75181568	NPPD	KCPL	22	1/1/2014	1/1/2024			\$ -	\$ -	\$ -	\$ -
			•	•	•	•	•		\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75181568	None					\$ -	\$ -	\$
					Total	\$ -	Ś -	Ś

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181568	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	10/1/2013	1/1/2015		
	Line - Thistle - Woodward 345 kV dbl Ckt PW	10/1/2013	1/1/2015		
	Line - Tuco - Woodward 345 kV line OKGE	10/1/2013	6/1/2014		
	Line - Tuco - Woodward 345 kV line SPS	10/1/2013	6/1/2014		

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch	ı
Reservation	Upgrade Name	DUN	EOC	Date	Available	ı
75181568	MOUNDRIDGE 138/115KV TRANSFORMER CKT 2	10/1/2013	12/1/2014			ı

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75181568	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KCPS	75199886	SECI	KCPL	50	8/1/2011	8/31/2013	4/1/2012	9/1/2013	\$ -	\$ 746,300	\$ -	\$ -
		•	•	•	•	•		•	\$ -	\$ 746,300	\$ -	\$ -

			Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75199886 None					\$ -	\$ -	\$
				Total	\$ -	\$ -	\$

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

						Earliest Start	Redispatch
Reservation	Upgrade Name			DUN	EOC	Date	Available
75199886	MOUNDRIDGE 138/115KV TRANS	FORMER CKT 2		10/1/2013	12/1/2014		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75199886	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - IODINE 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KCPS	75199893	SECI	KCPL	50	8/1/2011	8/31/2013	4/1/2012	9/1/2013	\$ -	\$ 746,300	\$ -	\$ -
									\$ -	\$ 746,300	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75199893	None					\$ -	\$ -	\$ -
•					Total	\$ -	\$ -	\$ -

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

						Earliest Start	Redispatch
Reservation	Upgrade Name			DUN	EOC	Date	Available
75199893	MOUNDRIDGE 138/115KV TRANS	FORMER CKT 2		10/1/2013	12/1/2014		

			Earliest Start	Redispatch
Upgrade Name	DUN	EOC	Date	Available
ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
WOODWARD - IODINE 138KV CKT 1	1/1/2010	1/1/2010		
WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		
3	ALEXANDER - PRATT 115KV CKT 1 ALEXANDER - SAWYER 3 115.00 115KV CKT 1 FLATROG3 138.00 - HARPER 138KV CKT 1 HUGO POWER PLANT - VALLIANT 345 KV AEPW HUGO POWER PLANT - VALLIANT 345 KV CKT 1 MEDICINE LODGE - SAWYER 115KV CKT 1 MEDICINE LODGE - SAWYER 115KV CKT 1 MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement NORTHWEST - TATONGA 345KV CKT 1 TATONGA - WOODWARD 345KV CKT 1 WOODWARD - IODINE 138KV CKT 1 WOODWARD - WOODWARD EN 138KV CKT 1	ALEXANDER - PRATT 115KV CKT 1 12/1/2009 ALEXANDER - SAWYER 3 115.00 115KV CKT 1 12/1/2009 FLATROGS 138.00 - HARPER 138KV CKT 1 12/1/2009 HUGO POWER PLANT - VALLIANT 345 KV AEPW 7/1/2012 HUGO POWER PLANT - VALLIANT 345 KV AEPW 7/1/2012 HUGO POWER PLANT - VALLIANT 345 KV AEPW 7/1/2012 LACYGNE - WEST GARDINER 345KV CKT 1 6/1/2006 MEDICINE LODGE - SAWYER 115KV CKT 1 12/1/2009 NORTH-WEST - TATONIGA 345KV CKT 1 12/1/2009 NORTH-WEST - TATONIGA 345KV CKT 1 1/1/2010 WOODWARD - WOODWARD 545KV CKT 1 1/1/2010 WOODWARD - WOODWARD EHV 138KV CKT 1 1/1/2010	Upgrade Name         DUN         EOC           ALEXANDER - PRATT 115KV CKT 1         12/1/2009         1/1/2014           ALEXANDER - SAWYER 3         115.00 115KV CKT 1         12/1/2009         1/1/2014           FLATRDG3         138.00 - HARPER 138KV CKT 1         12/1/2009         6/15/2013           HUGG POWER PLANT - VALLIANT 345 KV AEPW         7/1/2012         7/1/2012           HUGG POWER PLANT - VALLIANT 345KV CKT 1 WFEC         7/1/2012         1/1/2010           LACYGNE - WEST GARDNER 345KV CKT 1         6/1/2006         6/1/2006           MEDICINE LODGE - SAWYER 115KV CKT 1         12/1/2009         6/1/2013           NORTHWEST - TATONGA 345KV CKT 1         1/1/2010         1/1/2010           TATONGA - WOODWARD 345KV CKT 1         1/1/2010         1/1/2010           WOODWARD - OIDINE 138KV CKT 1         1/1/2010         1/1/2010           WOODWARD - WOODWARD EHV 138KV CKT 1         1/1/2010         1/1/2010	ALEXANDER - PRATT 115KV CKT 1 12/1/2009 1/1/2014  ALEXANDER - SAWYER 3 115.00 115KY CKT 1 12/1/2009 1/1/2014  FLATROGS 138.00 - HAPRER 138KV CKT 1 12/1/2009 1/1/2015  HUGO POWER PLANT - VALLIANT 345 KV AEPW 7/1/2012 7/1/2012  HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC 7/1/2012 7/1/2012  LACYGNE - WEST GARDMER 345KV CKT 1 6/1/2006 6/1/2006  MEDICINE LODGE - SAWYER 115KV CKT 1 12/1/2009 6/1/2013  NORTHWEST - TATONGA 345KV CKT 1 1/1/2010 1/1/2010  NORTHWEST - TATONGA 345KV CKT 1 1/1/2010 1/1/2010  WOODWARD - WOODWARD 545KV CKT 1 1/1/2010 1/1/2010  WOODWARD - WOODWARD ENSKY CKT 1 1/1/2010 1/1/2010

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	75200249	SPA	SECI	1	11/1/2013	12/31/2018	11/1/2013	12/31/2018	\$ 4,669	\$ -	\$ 4,669	\$ 7,186
									\$ 4,669	\$ -	\$ 4,669	\$ 7,186

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75200249	HAYS PLANT - SOUTH HAYS 115KV CKT 1 #2	6/1/2014	6/1/2016			\$ 4,669	\$ 4,734,006	\$ 7,186
					Total	\$ 4,669	\$ 4,734,006	\$ 7,186

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200249	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - RICE_CO 115KV CKT 1	10/1/2012	4/1/2013		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*34.5</sup> kV and lower underlying System Impacts and Upgrades have yet to be determined.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	75199561	OPPD	WR	6	2/1/2012	2/1/2017	6/1/2013	6/1/2018	\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75199561	None					\$ -	\$ -	\$
•					Total	\$ -	Ś -	Ś

Direct Assignment Facilities - The requested service is contingent upon completion of the following upgrades.

				Earliest Service	Redispatch	Allocat	ed E & C		
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		Total E 8	k C Cost
75199561	PAWNEE - LARNED 115 KV CKT 1	6/1/2013	6/1/2013			\$	706,833	\$	706,833
					Total	\$	706,833	\$	706,833

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75199561	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>For reservation 75199561, The Maximum Firm Import Capability before the PAWNEE - LARNED 115 KV CKT 1 upgrade is 7MW due to Larned 34.5/12.47kV transformer.

<sup>\*</sup>For reservation 75199561, PAWNEE - LARNED 115 KV CKT 1 upgrade assumes LARNED 115/12.47 KV transformer will be installed by Network Customer or Midwest Energy.

<sup>\*</sup>The estimated engineering and construction cost for the Pawnee to Larned 115 kV line has a 2009 year effective date. This estimate will be updated with a 2012 year effective date.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	75200582	SECI	SECI	23	1/1/2012	6/1/2026	1/1/2015	6/1/2029	\$ 51,632	\$ -	\$ 51,632	\$ 104,784
									\$ 51,632	\$ -	\$ 51,632	\$ 104,784

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75200582	HAYS PLANT - SOUTH HAYS 115KV CKT 1 #2	6/1/2014	6/1/2016			\$ 51,632	\$ 4,734,006	\$ 104,784
,					Total	\$ 51,632	\$ 4,734,006	\$ 104,784

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200582	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	10/1/2013	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt PW	10/1/2013	1/1/2015		Yes
	Line - Tuco - Woodward 345 kV line OKGE	10/1/2013	6/1/2014		Yes
	Line - Tuco - Woodward 345 kV line SPS	10/1/2013	6/1/2014		Yes

				Earliest Start	Redispatch
eservation	Upgrade Name	DUN	EOC	Date	Available
75200582	ALBION - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	FT RANDAL - MADISONCO 230.00 230KV CKT 1	10/1/2013	11/1/2014		
	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	6/1/2013	6/1/2013		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	KELLY - MADISONCO 230.00 230KV CKT 1	10/1/2013			
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - RICE_CO 115KV CKT 1	10/1/2012	4/1/2013		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
	NELIGH - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*34.5</sup> kV and lower underlying System Impacts and Upgrades have yet to be determined.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
LESM	75134451	NPPD	LES	10	10/1/2012	10/1/2017	6/1/2013	6/1/2018	\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75134451	None					\$ -	\$ -	\$ -
•					Total	ς -	ς -	\$ -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75134451	ALBION - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	NELIGH - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
MIDW	75200166	WR	WR	15	6/1/2012	6/1/2017	6/1/2016	6/1/2021	\$ 1,698,453	\$ -	\$ 1,698,453	\$ 2,529,347
		•			•	•		•	\$ 1.698,453	\$ -	\$ 1.698,453	\$ 2,529,347

				Earliest Start	Redispatch	Alloca	ted E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		Total E & C Cost	Requirements
75200166	HAYS PLANT - SOUTH HAYS 115KV CKT 1 #2	6/1/2014	6/1/2016		Yes	\$	1,698,453	\$ 4,734,006	\$ 2,529,347
•					Total	\$	1.698.453	\$ 4.734.006	\$ 2 529 347

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200166	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200166	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
MIDW	75200168	WR	WR	5	6/1/2012	6/1/2017	6/1/2016	6/1/2021	\$ 566,151	\$ -	\$ 566,151	\$ 843,116
									\$ 566,151	\$ -	\$ 566,151	\$ 843,116

				Earliest Start	Redispatch	Allocate	ed E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		Total E & C Cost	Requirements
75200168	HAYS PLANT - SOUTH HAYS 115KV CKT 1 #2	6/1/2014	6/1/2016		Yes	\$	566,151	\$ 4,734,006	\$ 843,116
					Total	\$	566,151	\$ 4,734,006	\$ 843,116

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200168	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200168	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
MIDW	75200171	WR	WR	5	6/1/2012	6/1/2017	6/1/2016	6/1/2021	\$ 566,151	\$ -	\$ 566,151	\$ 843,116
									\$ 566,151	\$ -	\$ 566,151	\$ 843,116

				Earliest Start	Redispatch	Allocate	d E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		Total E & C Cost	Requirements
75200171	HAYS PLANT - SOUTH HAYS 115KV CKT 1 #2	6/1/2014	6/1/2016		Yes	\$	566,151	\$ 4,734,006	\$ 843,116
					Total	\$	566,151	\$ 4,734,006	\$ 843,116

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200171	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200171	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
MIDW	75200180	WR	WR	5	6/1/2013	6/1/2018	6/1/2016	6/1/2021	\$ 566,151	\$ -	\$ 566,151	\$ 843,116
									\$ 566,151	\$ -	\$ 566,151	\$ 843,116

				Earliest Start	Redispatch	Allocated	IE&C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		Total E & C Cost	Requirements
75200180	HAYS PLANT - SOUTH HAYS 115KV CKT 1 #2	6/1/2014	6/1/2016		Yes	\$	566,151	\$ 4,734,006	\$ 843,116
					Total	Ś	566.151	\$ 4.734.006	\$ 843,116

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200180	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		

			Earliest Start	Redispatch
Upgrade Name	DUN	EOC	Date	Available
ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	ALEXANDER - PRATT 115KV CKT 1 ALEXANDER - SAWYER 3 115.00 115KV CKT 1 CIRCLE - RICE, CO 230KV CKT 1 FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1 FLATRDG3 138.00 - HARPER 138KV CKT 1 LACYONE - WEST GARDMER 345KV CKT 1 LYONS - WHEATLAND 115KV CKT 1 #1 LYONS - WHEATLAND 115KV CKT 1 #1 LYONS - WHEATLAND 115KV CKT 1 #1 MEDICINE LODGE - SAWYER 115KV CKT 1 MEDICINE LODGE - SAWYER 115KV CKT 1 MEDICINE LODGE 338/115KV TRANSFORMER CKT 1 Displacement NORTHWEST - TATONGA 345KV CKT 1 RICE, CO 230/115KV TRANSFORMER CKT 1 RICE, CO 230/115KV TRANSFORMER CKT 1	ALEXANDER - PRATT 115KV CKT 1  ALEXANDER - SAWYER 3 115.00 115KV CKT 1  ALEXANDER - SAWYER 3 115.00 115KV CKT 1  (INCLE - RICE, CO 230KV CKT 1  (INCLE - RICE, CO 230KV CKT 1  FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1  FLATRDG3 138.00 - HARPER 138KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER 245KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER 345KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER 345KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER 115KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER 115KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER - SAWYER 115KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER - SAWYER 115KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER - SAWYER 115KV CKT 1  (INCLE) ALEXANDER - WEST GARDNER - SAWYER - WEST GARDNER - WEST GARDN	Upgrade Name         DUN         EOC           ALEXANDER - PRATT 115KV CKT 1         12/1/2009         1/1/2014           ALEXANDER - SAWYER 3 115.00 115KV CKT 1         12/1/2009         1/1/2014           CIRCLE - RICE_CO 230KV CKT 1         10/1/2012         11/15/2012           FLATROG3 138.00 - MARPER 138KV CKT 1         12/1/2009         6/1/2013           FLATROG3 138.00 - HARPER 138KV CKT 1         12/1/2009         6/1/2013           LACYGNE - WEST GARDNER 345KV CKT 1         6/1/2006         6/1/2006           LYONS - WHEATLAND 115KV CKT 1 #1         10/1/2012         7/15/2013           MEDICINE LODGE - SAWYER 115KV CKT 1         12/1/2009         6/1/2013           MEDICINE LODGE 338/115KV TRANSFORMER CKT 1 Displacement         12/1/2009         6/1/2013           NORTHWEST - TATONGA 345KV CKT 1         11/1/2010         1/1/2010           RICE_CO 230/115KV TRANSFORMER CKT 1         10/1/2012         1/1/2010	Upgrade Name

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
MIDW	75200183	WR	WR	5	6/1/2013	6/1/2018	6/1/2016	6/1/2021	\$ 566,151	\$ -	\$ 566,151	\$ 843,116
									\$ 566,151	\$ -	\$ 566,151	\$ 843,116

				Earliest Start	Redispatch	Allocate	ed E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		Total E & C Cost	Requirements
75200183	HAYS PLANT - SOUTH HAYS 115KV CKT 1 #2	6/1/2014	6/1/2016		Yes	\$	566,151	\$ 4,734,006	\$ 843,116
•					Total	\$	566,151	\$ 4,734,006	\$ 843,116

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200183	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		

			Earliest Start	Redispatch
Jpgrade Name	DUN	EOC	Date	Available
ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
*LATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
*LATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
ACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
YONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
YONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	12/1/2009	6/1/2013		
NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
ATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
A A A A A A A A A A A A A A A A A A A	LEXANDER - PRATT 115KV CKT 1  LEXANDER - SAWYER 3 115.00 115KV CKT 1  IRICE - RICE, CO 230KV CKT 1  LATROS 3 138.00 - MEDICINE LODGE 138KV CKT 1  LATROS 3 138.00 - MEDICINE LODGE 138KV CKT 1  LATROS 3 138.00 - HAPPER 138KV CKT 1  ACYONE - WEST GARDNER 345KV CKT 1  YONS - WHEATLAND 115KV CKT 1 #1  YONS - WHEATLAND 115KV CKT 1 #2  REDICINE LODGE - SAWYER 115KV CKT 1  REDICINE LODGE - SAWYER 115KV TRANSFORMER CKT 1  REDICINE LODGE - SAWYER TISKV CKT 1	LEXANDER - PRATT 115KV CKT 1         12/1/2009           LEXANDER - SAWYER 3         115.00 115KV CKT 1         12/1/2009           RIGLE - RICE, CO 230KV CKT 1         10/1/2012         110/1/2012           LATROG3         138.00 - MEDICINE LODGE 138KV CKT 1         12/1/2009           LATROG3         138.00 - HARPER 138KV CKT 1         12/1/2009           ACYONE - WEST GARDNER 345KV CKT 1         6/1/2006           YONS - WHEATLAND 115KV CKT 1 #1         10/1/2012           YONS - WHEATLAND 115KV CKT 1 #2         10/1/2012           REDICINE LODGE - SAWYER 115KV CKT 1         12/1/2009           REDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement         12/1/2009           NORTHWEST - TATONGA 345KV CKT 1         1/1/2012           ICC, CO 230/115KV TRANSFORMER CKT 1         10/1/2012	DUN   EOC     EXANDER - PRATT 115KV CKT 1   12/1/2009   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2014   1/1/2015   1/1/2014   1/1/2015   1/1/2015   1/1/2016	DUN   EOC   Date

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
NPPM	75200206	NPPD	NPPD	1	12/1/2012	12/1/2017	6/1/2013	6/1/2018	\$ -	\$ 110,239	\$ -	\$ -
		•		•	•	•		•	\$ -	\$ 110.239	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75200206	None					\$ -	\$ -	\$
		Total	ς -	ς -	\$			

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75200206	ALBION - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	NELIGH - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
OMPA	75180762	CSWS	CSWS	50	6/1/2014	9/30/2018	6/1/2014	9/30/2018	\$ -	\$ -	\$ -	\$ -
		•	•	•	•	•	•	•	\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75180762	None					\$ -	\$ -	\$ -
•					Total	\$ -	Ś -	\$ -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75180762	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
OMPA	75196276	CSWS	OKGE	3	3/1/2012	12/31/2027	6/1/2013	4/1/2029	\$ -	\$ -	\$ -	\$ -
		•	•	•	•	•	•		\$ -	\$ -	\$ -	Ś -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75196276	None					\$ -	\$ -	\$
•		Total	\$ -	Ś -	Ś			

Construction Pending - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75196276	NORTHWEST 345/138/13.8KV TRANSFORMER CKT 3 Accelerated	6/1/2013	6/1/2015		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75196276	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
OPPM	75180047	NPPD	OPPD	18	12/1/2012	12/1/2017	6/1/2013	6/1/2018	\$ -	\$ -	\$ -	\$ -
		•	•	•	•	•	•	•	\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75180047	None					\$ -	\$ -	\$ -
•					Total	\$ -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75180047	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75180047	ALBION - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	NELIGH - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
SECI	75173900	SECI	SECI	80	7/1/2012	7/1/2032	6/1/2016	6/1/2036	\$ 478,813	\$ -	\$ 714,647	\$ 1,715,519
									\$ 478,813	\$ -	\$ 714,647	\$ 1,715,519

Reservation Upgrade Name		DUN		Earliest Start Date		Base Plan Funding for Wind	Directly Assigned	Allocated E & C Cost		Total Revenue Requirements
75173900 HAYS PLANT - SOUTH HAYS 115KV CKT	1 #2	6/1/2014	6/1/2016		Yes	\$ 478,813	\$ 235,8	4 \$ 714,647	\$ 4,734,006	\$ 1,715,51
					Total	\$ 478.813	\$ 235.8	A \$ 714.647	\$ 4.734.006	\$ 1.715.51

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75173900	Line - Clark County - Thistle 345 kV dbl Ckt	10/1/2013	1/1/2015		Yes
	Line - Hitchland - Woodward 345 kV dbl Ckt OKGE	10/1/2013	7/1/2014		Yes
	Line - Hitchland - Woodward 345 kV dbl Ckt SPS	10/1/2013	7/1/2014		Yes
	Line - Spearville - Clark County 345 kV dbl Ckt	10/1/2013	1/1/2015		Yes
	Line - Thistle - Wichita 345 kV dbl Ckt PW	10/1/2013	1/1/2015		Yes
	Line - Thistle - Wichita 345 kV dbl Ckt WERE	10/1/2013	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	10/1/2013	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt PW	10/1/2013	1/1/2015		Yes
	Line - Tuco - Woodward 345 kV line OKGE	10/1/2013	6/1/2014		Yes
	Line - Tuco - Woodward 345 kV line SPS	10/1/2013	6/1/2014		Yes
	XFR - Thistle 345/138 kV	10/1/2013	1/1/2015		Yes

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75173900	HARPER - MILAN TAP 138KV CKT 1 #1	10/1/2013	6/1/2015		Yes

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75173900	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
4.6 11. 1					

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
SPSM	75197996	SPS	SPS	42	6/1/2012	6/1/2045	1/1/2015	1/1/2048	\$ -	\$ -	\$ -	\$ -
		•		•	•	•		•	\$ -	\$ -	\$ -	\$ -

			Earliest Start	Redispatch	Allocated E & C		Total Revenue	
Reservation Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements	
75197996 None					\$ -	\$ -	\$	_
				Total	\$ -	\$ -	\$	1

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75197996	HITCHLAND INTERCHANGE () 230/115/13.2KV TRANSFORMER CKT 2	6/1/2021	6/1/2021		
	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	10/1/2013	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt PW	10/1/2013	1/1/2015		Yes
	Line - Tuco - Woodward 345 kV line OKGE	10/1/2013	6/1/2014		Yes
	Line - Tuco - Woodward 345 kV line SPS	10/1/2013	6/1/2014		Yes

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75197996	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	6/1/2015	6/1/2015		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
SPSM	75197998	SPS	SPS	29	6/1/2012	6/1/2032	1/1/2015	1/1/2035	\$ -	\$ -	\$ -	\$ -
		•	•	•	•	•		•	\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75197998	None					\$ -	\$ -	\$ -
•					Total	\$ -	ς -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75197998	HITCHLAND INTERCHANGE () 230/115/13.2KV TRANSFORMER CKT 2	6/1/2021	6/1/2021		
	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	10/1/2013	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt PW	10/1/2013	1/1/2015		Yes
	Line - Tuco - Woodward 345 kV line OKGE	10/1/2013	6/1/2014		Yes
	Line - Tuco - Woodward 345 kV line SPS	10/1/2013	6/1/2014		Yes

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75197998	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	6/1/2015	6/1/2015		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

Customer Study Number TNSK AG1-2011-029

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
TNSK	75108845	KCPL	ERCOTE	44	8/1/2011	6/1/2014	6/1/2013	6/1/2014	\$ -	\$ 832,519	\$ -	\$ -
									\$ -	\$ 832,519	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue	٦
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements	
75108845	None					\$ -	\$ -	\$	-
•					Total	\$ -	\$ -	\$	-

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

						Earliest Start	Redispatch
Reservation	Upgrade Name			DUN	EOC	Date	Available
75108845	IATAN - NASHUA 345KV CKT 1			10/1/2013	6/1/2015		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75108845	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	ASHDOWN REC (MILLWOOD) - OKAY 138KV CKT 1	7/1/2012	7/1/2012		
	ASHDOWN REC (MILLWOOD) - PATTERSON 138KV CKT 1	7/1/2012	7/1/2012		
	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FT RANDAL - MADISONCO 230.00 230KV CKT 1	10/1/2013	11/1/2014		
	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	6/1/2013	6/1/2013		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	7/1/2012	7/1/2012		
	KELLY - MADISONCO 230.00 230KV CKT 1	10/1/2013	11/1/2014		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	OKAY - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	SUB 110 - ORONOGO JCT SUB 167 - RIVERTON 161KV CKT 1	6/1/2011	6/1/2011		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - IODINE 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

Customer Study Number TNSK AG1-2011-030

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
TNSK	75108838	KCPL	ERCOTE	6	8/1/2011	6/1/2014	6/1/2013	6/1/2014	\$ -	\$ 146,123	\$ -	\$ -
									\$ -	\$ 146,123	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue	٦
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements	
75108838	None					\$ -	\$ -	\$	-
•					Total	\$ -	\$ -	\$	-

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75108838	IATAN - NASHUA 345KV CKT 1	10/1/2013	6/1/2015		

			Earliest Start	Redispatch
Upgrade Name	DUN	EOC	Date	Available
HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	7/1/2012	7/1/2012		
LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
MCNAB REC - TURK 115KV CKT 1	7/1/2012	7/1/2012		
NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
		HUGO POWER PLANT - VALLIANT 345 KV AEPW  7/1/2012 HUGO POWER PLANT - VALLIANT 345 KV CKT 1 WFEC  7/1/2012 HUGO POWER PLANT 34/5/138KV TRANSFORMER CKT 1  1/7/1/2012 LACYGNE - WEST GARDNER 345 KV CKT 1  MCNAB REC - TURK 115 KV CKT 1  NORTHWEST - TATONGA 345 KV CKT 1  1/1/2010	Upgrade Name         DUN         EOC           HUGO POWER PLANT - VALLIANT 345 KV AEPW         7/1/2012         7/1/2012           HUGO POWER PLANT - VALLIANT 345 KV CKT 1 WFEC         7/1/2012         7/1/2012           HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1         7/1/2012         7/1/2012           LACYGNE - WEST GARDNER 345KV CKT 1         6/1/2006         6/1/2006           MCNAB REC - TURK 115KV CKT 1         7/1/2012         7/1/2012           NORTHWEST - TATONGA 345KV CKT 1         1/1/2010         1/1/2010	Upgrade Name         DUN         EOC         Date           HUGO POWER PLANT - VALLIANT 345 KV AEPW         7/1/2012         7/1/2012           HUGO POWER PLANT - VALLIANT 345 KV CKT 1 WFEC         7/1/2012         7/1/2012           HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1         7/1/2012         7/1/2012           LACYGNE - WEST GARDNER 345KV CKT 1         6/1/2006         6/1/2006           MCNAB REC - TURK 115KV CKT 1         7/1/2012         7/1/2012           NORTHWEST - TATONGA 345KV CKT 1         1/1/2010         1/1/2010

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
WFEC	75179329	CSWS	WFEC	150	1/1/2012	1/1/2037	1/1/2015	1/1/2040	\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75179329	None					\$ -	\$ -	\$ -
•					Total	\$ -	Ś -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75179329	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	10/1/2013	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt PW	10/1/2013	1/1/2015		Yes
	Line - Tuco - Woodward 345 kV line OKGE	10/1/2013	6/1/2014		Yes
	Line - Tuco - Woodward 345 kV line SPS	10/1/2013	6/1/2014		Yes

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75179329	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	6/1/2015	6/1/2015		
	G03-05T 138.00 - PARADISE 138KV CKT 1	6/1/2010	6/1/2013		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1 WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010 1/1/2010	1/1/2010 1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

 Table 3 - Additional Details for Each Request Including All Facility Upgrades Required and Allocated Costs for Each Upgrade

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
WRGS	74977737	OKGE	WR	300	1/1/2016	6/1/2027			\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
74977737	None					\$ -	\$ -	\$
					Total	\$ -	Ś -	\$

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
74977737	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
WRGS	75021167	WR	WR	201	10/1/2012	1/1/2032	12/1/2014	3/1/2034	\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
75021167	None					\$ -	\$ -	\$ -
•					Total	\$ -	Ś -	\$ -

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

						Earliest Start	Redispatch
Reservation	Upgrade Name		D	DUN	EOC	Date	Available
75021167	MOUNDRIDGE 138/115KV TRANSFO	DRMER CKT 2		10/1/2013	12/1/2014		Yes

 ${\color{blue} \textbf{Construction Pending - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.} \\$ 

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75021167	CIRCLE - RICE_CO 230KV CKT 1	6/1/2013	6/1/2013		
	LYONS - RICE_CO 115KV CKT 1	6/1/2013	6/1/2013		
	LYONS - WHEATLAND 115KV CKT 1 #1	6/1/2013	7/15/2013		Yes
	LYONS - WHEATLAND 115KV CKT 1 #2	6/1/2013	7/15/2013		Yes
	RICE_CO 230/115KV TRANSFORMER CKT 1	6/1/2013	6/1/2013		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
75021167	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	1/1/2014		
	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	12/1/2009	1/1/2014		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/15/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - RICE_CO 115KV CKT 1	10/1/2012	4/1/2013		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	MEDICINE LODGE - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		

Transmission Owner	Upgrade	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)	Estimated Engineering & Construction Cost
		Tear down and rebuild of exisiting South Hays - Hays Plant 115 kV line.			
		Tentative plans include rebuilding on existing right-of-way with the			
		possibility of re-routing a portion of the line to new right-of-way as			
MIDW	HAYS PLANT - SOUTH HAYS 115KV CKT 1 #2	necessary.	6/1/2014	6/1/2016	\$4,734,005.62
		Install three series reactors in the Midway-St Joseph line at St Joseph			
MIPU	MIDWAY - ST JOE 161KV CKT 1 Reactor	Substation. The reactors will be rated 6% impedance and 1200 Amps.	6/1/2014	6/1/2015	\$440,733.00

Direct Assignment Facilities - The requested service is contingent upon completion of the following upgrades.

Transmission Owner	Upgrade		(DUN)	Estimated Date of Upgrade Completion (EOC)	Estimated Engineering & Construction Cost
MIDW	PAWNEE - LARNED 115 KV CKT 1	Build 1.5 mile 115 kV line from Pawnee to the City of Larned.	6/1/2013	6/1/2013	\$ 706,833

Construction Pending Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

Transmission Owner	Upgrade	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)
MIDW	CIRCLE - RICE_CO 230KV CKT 1	Convert from 115kV to 230kV operation	6/1/2013	6/1/2013
MIDW	LYONS - RICE_CO 115KV CKT 1	Rebuild 11.7 mile line	6/1/2013	6/1/2013
MIDW	RICE_CO 230/115KV TRANSFORMER CKT 1	Add 230/115kV Transformer	6/1/2013	6/1/2013
OKGE	NORTHWEST 345/138/13.8KV TRANSFORMER CKT 3 Accelerated	Install third 345/138 kV Bus Tie in Northwest Sub	6/1/2013	6/1/2015
WERE	LYONS - WHEATLAND 115KV CKT 1#1	Replace CTs	6/1/2013	7/15/2013
WERE	LYONS - WHEATLAND 115KV CKT 1#2	Rerate circuit to 1000 amps	6/1/2013	7/15/2013

Expansion Plan Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

s - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transm	ission customer.		,
Upgrade	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)
Line - Clark County - Thistle 345 kV dbl Ckt	from the Thistle 345 kV substation to the new Clark County substation. Build a new 345 kV substation at Thistle with a ring bus and necessary terminal equipment.	10/1/2013	1/1/2015
Line - Spearville - Clark County 345 kV dbl Ckt	from the Spearville substation to the new Clark County substation. Build the Clark County 345 kV substation with a ring bus and necessary terminal equipment.	10/1/2013	1/1/2015
XFR - Thistle 345/138 kV	Install a 400 MVA 345/138 kV transformer at the new 345 kV Thistle substation.	10/1/2013	1/1/2015
IATAN - NASHUA 345KV CKT 1	Tap Nashua 345kV bus in Hawthorn - St. Joseph 345 kV line. Build new 345 kV line from latan to Nashua,Add Nashua 345/161 kV	10/1/2013	6/1/2015
Line - Hitchland - Woodward 345 kV dbl Ckt OKGE	Build a new 92 mile double circuit 345 kV line with at least 3000 A capacity from the Woodward District EHV substation to the SPS interception from the Hitchland substation. Upgrade the Woodward District EHV substation with the necessary breakers and term	10/1/2013	7/1/2014
Line - Thistle - Woodward 345 kV dbl Ckt OKGE	Build a new 79 mile double circuit 345 kV line with at least 3000 A capacity from the Woodward District EHV substation to the Kansas/Oklahoma state border towards the Thistle substation. Upgrade the Woodward Distric EHV substation with the necessary by Paga	10/1/2013	1/1/2015
Line - Tuco - Woodward 345 kV line OKGE	Build new 345 kV line from Woodward EHV to Border - Project costs now include Border reactor substation	10/1/2013	6/1/2014
Line - Thistle - Wichita 345 kV dbl Ckt PW	from the Wichita substation to the new Thistle 345 kV substation.  Build a new 30 mile double circuit 345 kV line with at least 3000 A capacity	10/1/2013	1/1/2015
Line - Thistle - Woodward 345 kV dbl Ckt PW	the Woodward District EHV substation.	10/1/2013	1/1/2015
HITCHLAND INTERCHANGE () 230/115/13.2KV TRANSFORMER CKT 2	Add 2nd transformer	6/1/2021	6/1/2021
	Build 30 mile double circuit 345 kV line with at least 3000 A capacity from the Hitchland substation to the OGE interception point from the Woodward District EHV substation. Upgrade the Hitchland substation with		
Line - Hitchland - Woodward 345 kV dbl Ckt SPS	the necessary breakers and terminal equipme	10/1/2013	7/1/2014
Line - Tuco - Woodward 345 kV line SPS	Stateline. Install line reactor outside Border station and line reactors at Tuco.	10/1/2013	6/1/2014
Line - Thistle - Wichita 345 kV dbl Ckt WERE	Upgrade the Wichita substation with the necessary breakers and terminal equipment to accommodate two new 345 kV circuits from the new Thistle 345 kV substation	10/1/2013	1/1/2015
	Upgrade  Line - Clark County - Thistle 345 kV dbl Ckt  Line - Speanville - Clark County 345 kV dbl Ckt  XFR - Thistle 345/138 kV  LATAN - NASHUA 345KV CKT 1  Line - Hitchland - Woodward 345 kV dbl Ckt OKGE  Line - Thistle - Woodward 345 kV dbl Ckt OKGE  Line - Tristle - Woodward 345 kV dbl Ckt PW  Line - Thistle - Wichita 345 kV dbl Ckt PW  HTCHLAND INTERCHANGE () 230/115/13.2kV TRANSFORMER CKT 2  Line - Hitchland - Woodward 345 kV dbl Ckt SPS  Line - Hitchland - Woodward 345 kV dbl Ckt SPS	Upgrade  Solution  Build a new 36 file double circuit 345 kV line with at least 3000 A capacity from the Thistle 345 kV substation to the new Clark County substation. Build a new 36 kV substation at Thistle with a ring bus and necessary terminal equipment.  Line - Clark County - Thistle 345 kV dbl Ckt  terminal equipment.  Line - Spearville - Clark County 345 kV dbl Ckt  terminal equipment.  Line - Spearville - Clark County 345 kV dbl Ckt  terminal equipment.  Line - Spearville - Clark County 345 kV dbl Ckt  equipment.  Line - Spearville - Clark County 345 kV dbl Ckt  equipment.  Line - Spearville - Clark County 345 kV dbl Ckt  equipment.  Line - Spearville - Clark County 345 kV substation with a ring bus and necessary terminal equipment.  Line - Spearville - Clark County 345 kV substation with a ring bus and necessary terminal equipment.  Line - Spearville - Clark County 345 kV substation with a ring bus and necessary terminal equipment.  Line - Thistle - Woodward Datric EV substation with a ring bus and necessary terminal equipment.  Line - Hitchland - Woodward Strict EV substation with a least 3000 A capacity from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation to the Rys Interception from the Woodward Datric EV substation. Upgrade the Woodward Datric EV substation to the Rys Interest Substation.  Line - Thistle - Woodward 345 kV dbl Ckt OKGE  Build a new 36 kV line from Woodward EV to Border - Project costs now new 15 kV line with a least 3000 A capacity from the Wildshall and the Rys Interest Substation.  Line - Thistle - Woo	Upgrade  Solution  Build a new 86 mile double circuit 345 kV line with at least 300 A capacity from the Thistie 345 kV substation to the new Clark County substation. Build a new 36 mile double circuit 345 kV line with at least 300 A capacity from the Speanville colark County 345 kV dbl Ckt  Intel - Clark County - Thistie 345 kV dbl Ckt  Intel - Speanville - Clark County 345 kV dbl Ckt OKGE  Intel - Speanville - Clark County 345 kV dbl Ckt OKGE  Intel - Speanville - Clark County 345 kV dbl Ckt OKGE  Intel - Speanville - Clark County 345 kV dbl Ckt OKGE  Intel - Speanville - Clark County 345 kV dbl Ckt OKGE  Intel - Thistie - Woodward 345 kV dbl Ckt OKGE  Intel - Thistie - Woodward 345 kV dbl Ckt OKGE  Intel - Thistie - Woodward 345 kV dbl Ckt OKGE  Intel - Thistie - Woodward 345 kV dbl Ckt OKGE  Intel - Thistie - Woodward 345 kV dbl Ckt DW  Intel - Thistie - Woodward 345 kV dbl Ckt DW  Intel - Thistie - Woodward 345 kV dbl Ckt DW  Intel - Thistie - Woodward 345 kV dbl Ckt DW  Intel - Thistie - Woodward 345 kV dbl Ckt DW  Intel - Thistie - Woodward 345 kV dbl Ckt DW  Intel - Thisti

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

Transmission Owner	Upgrade	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)
		Install new 345/161 kV transformer at Kings River (Previous name Osage		
		Creek); Install 9 miles of 345 kV line from Shipe Road to East Rogers; Install		
		32 miles of 345 kV line from East Rogers to Kings River (previous Osage		
AEPW	Multi - Centerton - Osage Creek 345 kV	Creek).	6/1/2013	6/1/2016
		Install 9 miles of 161 kV from new Shipe Road Substation to East		
		Centerton Substation; Install 345/161 kV transformer at Shipe Road; Install		
AEPW	Multi - Flint Creek – Centerton 345 kV and Centerton- East Centerton 161 kV	18 miles of new 345 kV, 2-954 ACSR line.	6/1/2013	6/1/2014
MKEC	HARPER - MILAN TAP 138KV CKT 1 #1	Replace Wave Trap at Harper Substation	10/1/2013	6/1/2015
		Install second 138/115 kV transformer at Moundridge. Operate both		
WERE	MOUNDRIDGE 138/115KV TRANSFORMER CKT 2	138/115 kV transformers normally closed.	10/1/2013	12/1/2014

Notwork Ungrades requiring credits	per Attachment Z2 of the SPP OATT.

Network Upgrades rec	uiring credits per Attachment Z2 of the SPP OATT.			
Transmission Owner	Upgrade	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)
AEPW	ALUMAX TAP - BANN 138KV CKT 1	Replace six (6) 138 kV switches, five at Bann & one at Alumax Tap. Rebuild 0.67 miles of 1024 ACAR with 2156 ACSR. Replace wavetrap & jumpers @ Bann. Replace breaker 3300 @ Bann.	6/1/2008	6/1/2008
AEPW	ASHDOWN REC (MILLWOOD) - OKAY 138KV CKT 1	Recunductor and convert line to 138 kV and replace switches at Ashdown REC	7/1/2012	7/1/2012
AEPW	ASHDOWN REC (MILLWOOD) - PATTERSON 138KV CKT 1	Reconductor Line & Convert Line to 138 kV and convert Patterson station to breaker-and-a half cofiguration	7/1/2012	7/1/2012
AEPW	BANN - RED SPRINGS REC 138KV CKT 1	Replace 138 kV breakers 3300 & 3310  Reconductor 1.82 miles with ACCC. Replace wave trap jumpers at	7/1/2012	7/1/2012
AEPW	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 AEPW	Riverside.	6/1/2009	6/1/2009
AEPW AEPW	HUGO POWER PLANT - VALLIANT 345 KV AEPW  MCNAB REC - TURK 115KV CKT 1	Vallient 345 KV line terminal Build a new two mile, 138 kV, 1590 ACSR line section (operated at 115 kV) from Turk Substation to the existing Okay-Hope 115 kV line to form a Turk - Hope 115 kV line.	7/1/2012 7/1/2012	7/1/2012 7/1/2012
76.11	MANUEL TOTAL AND GAVE	Build two mile, 138 kV, 1590ACSR line section from Turk Sub to existing Okay-Hope 115 kV line and rebuild twelve miles of 115 kV line to Okay Sub	77172012	1/1/2012
AEPW	OKAY - TURK 138KV CKT 1	to 138 kV, 1590 ACSR , to form a Turk-Okay 138 kV line Build new Turk-SE Texarkana 138 kV line and add SE Texarkana 138 kV	7/1/2012	7/1/2012
AEPW	SE TEXARKANA - TURK 138KV CKT 1	terminal.	7/1/2012	7/1/2012
AEPW	SUGAR HILL - TURK 138KV CKT 1	Build new Turk-Sugar Hill 138 kV line and add Sugar Hill 138 kV terminal.	7/1/2012	7/1/2012
EMDE	SUB 110 - ORONOGO JCT SUB 167 - RIVERTON 161KV CKT 1	Reconductor Oronogo 59467 to Riverton 59469 with Bundled 556 ACSR	6/1/2011	6/1/2011
KACP	LACYGNE - WEST GARDNER 345KV CKT 1	KCPL Sponsored Project to Reconductor Line to be In-Service by 6/1/2006	6/1/2006	6/1/2006
MIDW	CIRCLE - RICE_CO 230KV CKT 1	Convert from 115kV to 230kV operation	10/1/2012	11/15/2012
MIDW	LYONS - RICE_CO 115KV CKT 1 RICE_CO 230/115KV TRANSFORMER CKT 1	Rebuild 11.7 mile line Add 230/115kV Transformer	10/1/2012 10/1/2012	4/1/2013 11/15/2012
MKEC	ALEXANDER - PRATT 115KV CKT 1	Rebuild line	12/1/2009	1/1/2014
MKEC	ALEXANDER - SAWYER 3 115.00 115KV CKT 1	Rebuild line	12/1/2009	1/1/2014
MKEC	CLIFTON - GREENLEAF 115KV CKT 1	Rebuild 14.4 miles	6/1/2011	6/1/2013
MKEC	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	Rebuild 8.05 mile line	12/1/2009	6/1/2013
MKEC	FLATRDG3 138.00 - HARPER 138KV CKT 1	Rebuild 24.15 mile line	12/1/2009	6/15/2013
MKEC	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	Rebuild 43.5% Ownership of 20.9 miles	6/1/2013	6/1/2013
MKEC	MEDICINE LODGE - SAWYER 115KV CKT 1	Rebuild line	12/1/2009	6/1/2013
MKEC	MEDICINE LODGE 138/115KV TRANSFORMER CKT 1 Displacement	Upgrade transformer	12/1/2009	6/1/2013
NPPD	ALBION - PETERSBURG 115KV CKT 1	Replace Breaker Switch 1106-D and jumpers at Albion. Replace main bus at Petersburg. Upgrade and replace transmission structures on 115 kV lineto facilitate 100 degrees Centigrade line operation.  Raise structures and line clearances as necessary to re-rate the	1/1/2013	1/1/2013
NPPD	FT RANDAL - MADISONCO 230.00 230KV CKT 1	transmission line to 320MVA Raise structures and line clearances as necessary to re-rate the	10/1/2013	11/1/2014
NPPD	KELLY - MADISONCO 230.00 230KV CKT 1	transmission line to 320MVA Replace Breaker 1106, jumpers, and 115 kV Switch 1106-D2 at Neligh. Replace main bus at Petersburg. Upgrade and replace transmission structures on 115 kV lineto facilitate 100 degrees Centigrade line	10/1/2013	11/1/2014
NPPD	NELIGH - PETERSBURG 115KV CKT 1	operation.	1/1/2013	1/1/2013
OKGE	BEELINE - EXPLORER GLENPOOL 138KV CKT 1	Reconductor .92miles of line with Drake ACCC/TW.	6/1/2009	6/1/2009
OKGE	EXPLORER GLENPOOL - RIVERSIDE STATION 138KV CKT 1 OKGE	Reconductor 1.82 miles line with Drake ACCC/TW.	6/1/2009	6/1/2009
OKGE	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	Build 138kV Terminal.	1/1/2012	1/1/2012
OKGE OKGE	KNOBHILL (KNOBHIL4) 138/69/13.2KV TRANSFORMER CKT 1 NORTHWEST - TATONGA 345KV CKT 1	Replace bus tie with 100MVA transformer Build 345 kV line	6/1/2006 1/1/2010	6/1/2008 1/1/2010
OKGE	TATONGA - WOODWARD 345KV CKT 1	Build 345 kV line Build 345 kV line	1/1/2010	1/1/2010
OKGE	WOODWARD - IODINE 138KV CKT 1	Tap lodine to Woodward 138 kV line	1/1/2010	1/1/2010
OKGE	WOODWARD - NOODWARD EHV 138KV CKT 1	Build .5 miles of 138 kV and install terminal equipment	1/1/2010	1/1/2010
OKGE	WOODWARD - WOODWARD EHV 138KV CKT 2	Build .5 miles of 138 kV and install terminal equipment	1/1/2010	1/1/2010
OKGE	WOODWARD 345/138KV TRANSFORMER CKT 1	Install 345/138 kV XF	1/1/2010	1/1/2010
SPS	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	Replace wavetrap at Harrington East	6/1/2015	6/1/2015
WERE	DEARING 138KV Capacitor	Dearing 138 kV 20 MVAR Capacitor Addition	6/1/2012	6/1/2012
WERE	LYONS - WHEATLAND 115KV CKT 1#1	Replace CTs	10/1/2012	7/15/2013
WERE	LYONS - WHEATLAND 115KV CKT 1#2	Rerate circuit to 1000 amps	10/1/2012	7/15/2013
WFEC	CANTON - TALOGA 69KV CKT 1	UPGRADE CANTON TO TALOGA TO 336.4	6/1/2011	6/1/2013
WFEC	G03-05T 138.00 - PARADISE 138KV CKT 1	Upgrade Paradise to G03-05T to 1113	6/1/2010	6/1/2013
WFEC	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	Build approximately 6 miles of 138kV.	1/1/2012	1/1/2012
WFEC	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	New 19 miles 345 KV	7/1/2012	7/1/2012
WFEC	HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	New 345/138 kv Auto	7/1/2012	7/1/2012
WFEC	TALOGA (TALOGA) 138/69/13.8KV TRANSFORMER CKT 1	Auto XFMR 56 to 112MVA	10/1/2010	6/1/2013

## Table 5 - Third Party Facility Constraints

Transmission Owner	UpgradeName	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)	Estimated Engineering & Construction Cost
	None				