# Aggregate Facility Study SPP-2012-AG1-AFS-6

1/03/2014

SPP Engineering, SPP Transmission Service Studies



# **Table of Contents**

Table of Contents	1
Executive Summary	2
Introduction	3
Financial Analysis	5
Third Party Facilities	6
Study Methodology	7
Description	7
Model Development	7
Transmission Request Modeling	8
Transfer Analysis	8
Curtailment and Redispatch Evaluation	8
Study Results	9
Study Analysis Results	9
Example A:	10
Example B:	11
Example C:	11
Study Definitions	12
Conclusion	13
Appendix A	14
BASE CASE SETTINGS:	14
ACCC CASE SETTINGS.	1.4

# **Executive Summary**

Pursuant to Attachment Z1 of the Southwest Power Pool, Inc. (SPP) Open Access Transmission Tariff (OATT), 2515 MW of long-term transmission service requests have been studied in this Aggregate Facility Study (AFS). The principal objective of the AFS is to identify system problems and potential modifications necessary to facilitate these transfers while maintaining or improving system reliability, as well as summarizing the operating limits and determination of the financial characteristics associated with facility upgrades. A highly tangible benefit of studying transmission requests aggregately under the SPP OATT Attachment Z1 is the sharing of costs among Transmission Customers using the same facility. Facility upgrade costs are allocated on a prorated basis to all requests positively impacting any individual overloaded facility.

Attachment Z2 further provides for facility upgrade cost recovery by stating: "Transmission Customers paying Directly Assigned Upgrade Costs for Service Upgrades or that are in excess of the Safe Harbor Cost Limit for Network Upgrades associated with new or changed Designated Resources and Project Sponsors paying Directly Assigned Upgrade Costs for Sponsored Upgrades shall receive revenue credits in accordance with Attachment Z2. Generation Interconnection Customers paying for Network Upgrades shall receive credits for new transmission service using the facility as specified in Attachment Z1."

- The AFS determined that the total assigned facility upgrade Engineering and Construction (E&C) cost is \$1.1 million. Additionally, \$26 thousand of assigned E&C cost for third party facility upgrades are assignable to the customer.
- Total upgrade levelized revenue requirements for all transmission requests after consideration of potential base plan funding is \$1.1 million.

To accommodate the requested SPP Transmission Service, third party facilities must be upgraded when the third party transmission provider determines that they are constrained. Third party facilities include both first-tier neighboring facilities outside SPP and Transmission Owner facilities within SPP that are not under the SPP OATT. In this AFS, third party facilities were identified. Total E&C cost estimates for required third party facility upgrades are applicable.

SPP will tender an Aggregate Completion Agreement on January 3, 2014. This will open a 15-day window for Customer response. To remain in the Aggregate Transmission Service Study (ATSS), SPP must receive from the Customer by January 18, 2014, an executed Aggregate Completion Agreement. The Aggregate Completion Agreement will list options the Customer must choose to clarify their commitment to remain in the ATSS. The only action required on OASIS is to withdraw the request or leave the request in study mode.

At the conclusion of the ATSS, Service Agreements for each request for service will be tendered identifying the terms and conditions of the confirmed service.

If Customers withdraw from the ATSS after posting of this AFS, the AFS will be re-performed to determine final cost allocation and Available Transmission Capability (ATC) in consideration of the remaining ATSS participants. All allocated revenue requirements for facility upgrades are assigned to the Customer in the AFS data tables. Potential base plan funding allowable is contingent upon validation of designated resources meeting Attachment J, Section III B criteria.

## Introduction

Important milestones and dates in SPP's Aggregate Transmission Study process:

- In 2005, the Federal Energy Regulatory Commission (FERC) accepted SPP's proposed Aggregate Transmission Study procedures in Docket ER05-109.
- In 2008, in Docket ER08-1379-000 SPP filed with FERC to pair open seasons closing during January 2010 with an effective date of August 9, 2008.
- In January 2010, in Docket ER10-659-000 SPP filed with FERC to extend its current practice of pairing open seasons through January 31, 2011, with an effective date of January 28, 2010.
- In March 2010, in Docket ER10-659-000 FERC issued a letter order accepting SPP's proposal to continue to pair open seasons through January 31, 2011, effective January 28, 2010.
- All requests for long-term transmission service with a signed study agreement received before January 1, 2012 for 2012-AG1 have been included in this first Aggregate Transmission Service Study (ATSS) of 2012.

Approximately 2515 MW of long-term Transmission Service was studied in this Aggregate Facility Study (AFS), and over \$1.1 million in transmission upgrades is proposed. The results of the AFS are detailed in Tables 1 through 6. Detailed results depict individual upgrade costs by study and potential base plan allowances determined by Attachments J and Z1. The OATT may be accessed at SPP's website by going to SPP.org>Org Groups>Governing Documents.

To understand the extent to which Base Plan Upgrades may be applied to both Point-to-Point (PTP) and Network Transmission Services, it is necessary to highlight the definition of Designated Resource. Per Section 1.9a of the SPP OATT, a Designated Resource is:

"[a]ny designated generation resource owned, purchased or leased by a Transmission Customer to serve load in the SPP Region. Designated Resources do not include any resource, or any portion thereof, that is committed for sale to third parties or otherwise cannot be called upon to meet the Transmission Customer's load on a non-interruptible basis."

Network and PTP service has potential for base plan funding if the conditions for classifying upgrades associated with designated resources as Base Plan Upgrades as defined in Section III.B of Attachment J are met.

Pursuant to Attachment J, Section III B of the SPP OATT, the Transmission Customer must provide SPP information necessary to verify that the new or changed Designated Resource meets the following conditions:

- 1. Transmission Customer's commitment to the requested new or changed Designated Resource must have a duration of at least five years.
- 2. During the first year the Designated Resource is planned to be used by the Transmission Customer, the accredited capacity of the Transmission Customer's existing Designated Resources plus the lesser of:
  - a. The planned maximum net dependable capacity applicable to the Transmission Customer or
  - b. The requested capacity; shall not exceed 125% of the Transmission Customer's projected system peak responsibility determined pursuant to SPP Criteria 2.

According to Attachment Z1 Section VI.A, PTP customers pay the higher of the monthly transmission access charge (base rate) or the monthly revenue requirement associated with the assigned facility upgrades, including any prepayments for redispatch required during construction.

Network Integration Service Customers pay the total monthly transmission access charges and the monthly revenue requirement associated with the facility upgrades, including any prepayments for redispatch during construction.

Transmission Customers paying for a directly assigned Network Upgrade shall receive credits for new transmission service using the facility as specified in Attachment Z2.

Facilities identified as limiting the requested Transmission Service have been reviewed to determine the required in-service date of each Network Upgrade. The year that each Network Upgrade is required to accommodate a request is determined by interpolating between the applicable model years given the respective loading data. Both previously assigned facilities and the facilities assigned to this request for Transmission Service were evaluated.

In some instances, due to lead times for engineering and construction, Network Upgrades may not be available when required to accommodate a request for Transmission Service. When this occurs, the ATC with available Network Upgrades will be less than the capacity requested during either a portion of or all of the requested reservation period. As a result, the lowest seasonal allocated ATC within the requested reservation period will be offered to the Transmission Customer on an applicable annual basis as listed in Table 1. The ATC may be limited by transmission owner planned projects, expansion plan projects, or Customer assigned upgrades.

Some constraints identified in the AFS were not assigned to the Customer because SPP, the Transmission Provider, determined that upgrades are not required due to various reasons or the Transmission Owner has construction plans pending for these upgrades. These facilities are listed by reservation in Table 3. This table also includes constrained facilities in the current planning horizon that limit the rollover rights of the Transmission Customer. Table 6 lists possible redispatch pairs to allow start of service prior to completion of assigned Network Upgrades. Table 7 (if applicable) lists

deferment of expansion plan projects with different upgrades with the new required in service date as a result of this AFS.

By taking the transmission service subject to interim redispatch, the Transmission Customer agrees to provide interim redispatch. Once the Transmission Provider identifies the possible redispatch pairs, the Transmission Customer can enter into bilateral agreements to provide redispatch. Should the need to implement redispatch arise in order to maintain Network reliability, it is up to the Transmission Customer to contact parties with whom they have entered into redispatch agreements to implement that service. Such redispatch shall occur in advance of curtailment of other firm reservations impacting these constraints. In the absence of implementation of interim redispatch as requested by the Transmission Provider for Transmission Customer transactions resulting in overloads on limiting facilities, the Transmission Provider shall curtail the Transmission Customers schedule.

# **Financial Analysis**

The AFS utilizes the allocated Customer's E&C cost in a present worth analysis to determine the monthly levelized revenue requirement of each facility upgrade over the term of the reservation. In some cases, Network Upgrades cannot be completed within the requested reservation period, thus deferred reservation periods will be utilized in the present worth analysis. If the Customer chose Option 2, Redispatch, in the Aggregate Completion Agreement, the present worth analysis of revenue requirements will be based on the deferred term with redispatch in the subsequent AFS. The upgrade levelized revenue requirement includes interest, depreciation, and carrying costs.

Each request for Transmission Service is evaluated independently as the cost associated with each Network Upgrade is assigned to a request. When facilities are upgraded throughout the reservation period, the Transmission Customer shall 1) pay the total E&C costs and other annual operating costs associated with the new facilities, and 2) receive credits associated with the depreciated book value of removed usable facilities; salvage value of removed non-usable facilities; and the carrying charges, excluding depreciation, associated with all removed usable facilities based on their respective book values.

In the event that the engineering and construction of a previously assigned Network Upgrade may be accelerated, with no additional upgrades, to accommodate a new request for Transmission Service, the levelized present worth of only the incremental expenses though the reservation period of the new request, excluding depreciation, shall be assigned to the new request. These incremental expenses, excluding depreciation, include:

- 1. The levelized difference in present worth of the engineering and construction expenses given the change in date to complete construction to account for additional interest expense and reduced engineering and construction expense due to inflation,
- 2. The levelized present worth of all expediting fees, and

- 3. The levelized present worth of the incremental annual carrying charges, excluding depreciation and interest, during the new reservation period taking into account both:
  - a. The reservation in which the project was originally assigned, and
  - b. A reservation, if any, in which the project was previously accelerated.

In the case of a Base Plan Upgrade being displaced or deferred by an earlier in service date for a requested upgrade, achievable base plan avoided revenue requirements shall be determined per Attachment J, Section VII.B methodology. A deferred Base Plan Upgrade is defined as a different requested Network Upgrade needed at an earlier date that negates the need for the initial Base Plan Upgrade within the planning horizon. A displaced Base Plan Upgrade is defined as the same Network Upgrade being displaced by a requested upgrade needed at an earlier date.

A 40-year service life assumption is utilized for Base Plan funded projects, unless another assumption is provided by the Transmission Owner. A present worth analysis of revenue requirements on a common year basis between the Base Plan and Requested Upgrades was performed to determine avoided Base Plan revenue requirements due to the displacement or deferral of the Base Plan Upgrade by the Requested Upgrade. The difference in present worth between the Base Plan and Requested Upgrades is assigned to the transmission requests impacting this upgrade based on the displacement or deferral.

# Third Party Facilities

For third party facilities listed in Table 3 and Table 5, the Transmission Customer is responsible for funding the necessary upgrades of these facilities per Section 21.1 of the Transmission Provider's OATT. In this AFS, third party facilities were identified. Total E&C cost estimates for required third party facility upgrades are applicable. The Transmission Provider will undertake reasonable efforts to assist the Transmission Customer in making arrangements for necessary engineering, permitting, and construction of the third party facilities. Third party facilities upgrade E&C cost estimates are not utilized to determine the present worth value of levelized revenue requirements for SPP system Network Upgrades.

All modeled facilities within the Transmission Provider system were monitored during the development of this study, as well as certain facilities in first-tier neighboring systems. Third party facilities must be upgraded when it is determined that they are overloaded while accommodating the requested Transmission Service. An agreement between the Customer and third party owner detailing the mitigation of the third party impact must be provided to the Transmission Provider prior to tendering of a Transmission Service Agreement. These facilities also include those owned by members of the Transmission Provider who have not placed their facilities under the Transmission Provider's OATT. Upgrades on the Southwest Power Administration network requires prepayment of the upgrade cost prior to construction of the upgrade.

Third party facilities are evaluated for only those requests whose load sinks within the SPP footprint. The Customer must arrange for study of third party facilities for load that sinks outside the SPP footprint with the applicable Transmission Providers.

# Study Methodology

#### **Description**

The facility study analysis was conducted to determine the steady-state impact of the requested service on the SPP and first tier non-SPP control area systems. The steady-state analysis was performed to ensure current SPP Criteria and NERC Reliability Standards requirements are fulfilled. SPP conforms to NERC Reliability Standards, which provide strict requirements related to voltage violations and thermal overloads during normal conditions and during a contingency. NERC Standards require all facilities to be within normal operating ratings for normal system conditions and within emergency ratings after a contingency.

Normal operating ratings and emergency operating ratings monitored are Rate A and B in the SPP Model Development Working Group (MDWG) models, respectively. The upper bound and lower bound of the normal voltage range monitored is 105% and 95%. The upper bound and lower bound of the emergency voltage range monitored is 105% and 90%. Transmission Owner voltage monitoring criteria is used if more restrictive. The SPS Tuco 230 kV bus voltage is monitored at 92.5% due to pre-determined system stability limitations. The WERE Wolf Creek 345 kV bus voltage is monitored at 103.5% and 98.5% due to transmission operating procedure.

The contingency set includes all SPP control area branches and ties 69 kV and above; first tier non-SPP control area branches and ties 115 kV and above; any defined contingencies for these control areas; and generation unit outages for the control areas with SPP reserve share program redispatch. The monitor elements include all SPP control area branches, ties, and buses 69 kV and above, and all first tier non-SPP control area branches and ties 115 kV and above. Voltage monitoring was performed for SPP control area buses 69 kV and above.

A 3 % transfer distribution factor (TDF) cutoff was applied to all SPP control area facilities. For first tier non-SPP control area facilities, a 3 % TDF cutoff was applied to AECI, AMRN (Ameren), and ENTR (Entergy) control areas. A 2 % TDF cutoff was applied to WAPA. For voltage monitoring, a 0.02 per unit change in voltage must occur due to the transfer or modeling upgrades to be considered a valid limit to the transfer.

# **Model Development**

SPP used seven seasonal models to study the aggregate transfers over a variety of requested service periods. The following SPP Transmission Expansion Plan 2012 Build 1 Cases were used to study the impact of the requested service on the transmission system:

2013/14 Winter Peak (13WP) 2014 Summer Peak (14SP) 2014/2015 Winter Peak (14WP)

2018 Summer Peak (18SP) 2018/19 Winter Peak (18WP) 2023 Summer Peak (23SP) 2023/2024 Winter Peak (23WP)

The Summer Peak models apply to June through September and the Winter Peak models apply to December through March.

The chosen base case models were modified to reflect the current modeling information. One group of requests was developed from the aggregate to model the requested service. From the seasonal models, two system scenarios were developed. Scenario 0 includes projected usage of transmission included in the SPP 2012 Series Cases. Scenario 5 includes transmission service not already included in the SPP 2012 Series Cases.

## **Transmission Request Modeling**

Network Integration Transmission Service requests are modeled as Generation to Load transfers in addition to Generation to Generation transfers. Network Integration Transmission Service requests are modeled as Generation to Load transfers in addition to Generation to Generation because the requested Network Integration Transmission Service is a request to serve network load with the new designated network resource, and the impacts on Transmission System are determined accordingly. Point-To-Point Transmission Service requests are modeled as Generation to Generation transfers. Generation to Generation transfers are accomplished by developing a post-transfer case for comparison by dispatching the request source and redispatching the request sink.

## **Transfer Analysis**

Using the selected cases both with and without the requested transfers modeled, the PSS/E Activity ACCC was run on the cases and compared to determine the facility overloads caused or impacted by the transfer. Transfer distribution factor cutoffs (SPP and 1<sup>st</sup>-Tier) and voltage threshold (0.02 change) were applied to determine the impacted facilities. The PSS/E options chosen to conduct the analysis can be found in Appendix A.

## Curtailment and Redispatch Evaluation

During any period in which SPP determines that a transmission constraint exists on and may impair Transmission System reliability, SPP will take whatever actions are reasonably necessary to maintain reliability. If SPP determines Transmission System reliability can be maintained by redispatching resources, it will evaluate the interim curtailment of existing confirmed service or interim redispatch of units to provide service prior to completion of any assigned Network Upgrades. Any redispatch may not unduly discriminate between the Transmission Owners' use of the Transmission System on behalf of their Native Load Customers and any Transmission Customer's use of the Transmission System to serve its designated load. Redispatch was evaluated to provide only interim service during the time frame prior to completion of any assigned Network Upgrades. Curtailment of existing confirmed service is evaluated to provide only interim service. Curtailment of existing confirmed service is only evaluated at the request of the transmission Customer.

SPP determined potential relief pairs to relieve the incremental MW impact on limiting facilities as identified in Table 6. Using the selected cases where the limiting facilities were identified, potential incremental and decremental units were identified by determining the generation amount available for increasing and decreasing from the units generation amount, maximum generation amount, and minimum generation amount. If the incremental or decremental amount was greater than 1 MW, the unit was considered as a potential incremental or decremental unit.

Generation shift factors were calculated for the potential incremental and decremental units using Managing and Utilizing System Transmission (MUST). Relief pairs from the generation shift factors for the incremental and decremental units with a greater than 3% TDF on the limiting constraint were determined from the incremental units with the lowest generation shift factors and decremental units with highest generation shift factors. If the aggregate redispatch amount for the potential relief pair was determined to be three times greater than the lower of the increment or decrement, then the pair was determined not to be feasible and is not included. Transmission Customers can request SPP to provide additional relief pairs beyond those determined. The potential relief pairs were not evaluated to determine impacts on limiting facilities in the SPP and first tier systems. The SPP Reliability Coordinator would call upon the redispatch requirements before implementing NERC TLR Level 5a.

The Aggregate Study analyzes the most probable contingencies and does not account for every situation that may be encountered in real-time operation. Because of this, it is possible that the customer may be curtailed under certain system conditions to allow system operators to maintain the reliability of the transmission network.

# **Study Results**

## **Study Analysis Results**

Tables 1 through 6 contain the AFS steady-state analysis results. Table 1 identifies the participating long-term Transmission Service requests included in the AFS. This table lists deferred start and stop dates both with and without redispatch (based on Customer selection of redispatch if available) and the minimum annual allocated ATC without upgrades and season of first impact.

Table 2 identifies total E&C cost allocated to each Transmission Customer, letter of credit requirements, third party E&C cost assignments, potential base plan E&C funding (lower of allocated E&C or Attachment J Section III B criteria), point-to-point base rate charge, total revenue requirements for assigned upgrades with consideration of potential base plan funding, and final total cost allocation to the Transmission Customer. In addition, Table 2 identifies SWPA upgrade costs which require prepayment in addition to other allocated costs.

Table 3 provides additional details for each request including all assigned facility upgrades required, allocated E&C costs, allocated revenue requirements for upgrades, upgrades not assigned to the Customer but required for service to be confirmed, credits to be paid for previously assigned AFS or Generation Interconnection Network Upgrades, and any required third party upgrades.

Table 4 lists all upgrade requirements with associated solutions needed to provide Transmission Service for the AFS, minimum ATC per upgrade with season of impact, earliest date upgrade is required (DUN), estimated date the upgrade will be completed, in service (EOC), and estimated E&C cost.

Table 5 lists identified third party constrained facilities.

Table 6 identifies potential redispatch pairs available to relieve the aggregate impacts on identified constraints to prevent deferral of start of service. MW amounts listed for redispatch are maximum values observed in a long term study and may only be available in a reduced amount or unavailable at any given time.

Table 7 (if applicable) identifies deferred expansion plan projects that were replaced with requested upgrades at earlier dates.

The potential base plan funding allowable is contingent on meeting each of the conditions for classifying upgrades associated with designated resources as Base Plan Upgrades as defined in Section III.B of Attachment J. If the additional capacity of the new or changed Designated Resource exceeds the 125% resource to load forecast for the year of start of service, the requested resource is not eligible for base plan funding of required Network Upgrades and the full cost of the upgrades is assignable to the Customer.

If the request is for wind generation, the total requested capacity of wind generation plus existing wind generation capacity shall not exceed 20% of the customer's projected system peak responsibility in the first year the Designated Resource is planned to be used by the customer. If the five-year term and 125% resource to load criteria are met, (as well as the 20% wind resource to load criteria for wind generation requests) the requested capacity is multiplied by \$180,000 to determine the potential base plan funding allowable. The maximum potential base plan funding allowable may be less than the potential base plan funding allowable, due to the E&C cost allocated to the customer being lower than the potential amount allowable to the Customer. The Customer is responsible for any assigned upgrade costs in excess of potential base plan E&C funding allowable. Network Upgrades required for wind generation requests located in a zone other than the Customer POD shall be allocated as 67% base plan region-wide charge and 33% directly assigned to the Customer.

Regarding application of base plan funding for PTP requests, if PTP base rate exceeds upgrade revenue requirements without taking into effect the reduction of revenue requirements by potential base plan funding, then the base rate revenue pays back the Transmission Owner for upgrades and no base plan funding is applicable as the access charge must be paid as it is the higher of "OR" pricing.

However, if initially the upgrade revenue requirements exceed the PTP base rate, then potential base plan funding would be applicable. The test of the higher of "OR" pricing would then be made against the remaining assignable revenue requirements versus PTP base rate. Examples are as follows:

#### **Example A:**

E&C allocated for upgrades is \$74 million with revenue requirements of \$140 million and PTP base rate of \$101 million. Potential base plan funding is \$47 million, with the difference of \$27 million

E&C assignable to the Customer. If the revenue requirements for the assignable portion is \$54 million and the PTP base rate is \$101 million, the Customer will pay the higher amount (so-called "or pricing") of \$101 million base rate of which \$54 million revenue requirements will be paid back to the Transmission Owners for the upgrades, and the remaining revenue requirements of \$86 million (\$140 million less \$54 million) will be paid by base plan funding.

#### **Example B:**

E&C allocated for upgrades is \$74 million with revenue requirements of \$140 million and PTP base rate of \$101 million. Potential base plan funding is \$10 million with the difference of \$64 million E&C assignable to the Customer. If the revenue requirements for this assignable portion is \$128 million and the PTP base rate is \$101 million, the Customer will pay the higher amount of \$128 million revenue requirements to be paid back to the Transmission Owners, and the remaining revenue requirements of \$12 million (\$140 million less \$128 million) will be paid by base plan funding.

#### **Example C:**

E&C allocated for upgrades is \$25 million with revenue requirements of \$50 million and PTP base rate of \$101 million. Potential base plan funding is \$10 million. Base plan funding is not applicable as the higher amount of PTP base rate of \$101 million must be paid and the \$50 million revenue requirements will be paid from this.

The 125% resource to load determination is performed on a per request basis and is not based on a total of Designated Resource requests per Customer. A footnote will provide the maximum resource designation allowable for base plan funding consideration per Customer basis per year.

Base plan funding verification requires that each Transmission Customer with potential for base plan funding provide SPP attestation statements verifying that the firm capacity of the requested Designated Resource is committed for a minimum five year duration.

### **Study Definitions**

- The date upgrade needed date (DUN) is the earliest date the upgrade is required to alleviate a constraint considering all requests.
- End of construction (EOC) is the estimated date the upgrade will be completed and in service.
- Total engineering and construction cost (E&C) is the upgrade solution cost as determined by the Transmission Owner.
- The Transmission Customer's allocation of the E&C cost is based on the request (1) having an impact of at least 3% on the limiting element, and (2) having a positive impact on the upgraded facility.
- Minimum ATC is the portion of the requested capacity that can be accommodated without upgrading facilities.
- Annual ATC allocated to the Transmission Customer is determined by the least amount of allocated seasonal ATC within each year of a reservation period.

## Conclusion

The results of the AFS show that limiting constraints exist in many areas of the regional Transmission System. Due to these constraints, Transmission Service cannot be granted unless noted in Table 3.

The Transmission Provider will tender an Aggregate Completion Agreement on January 3, 2014. This will open a 15-day window for Customer response. To remain in the Aggregate Transmission Service Study (ATSS), the Transmission Provider must receive from the Transmission Customer by January 18, 2014, an executed Aggregate Completion Agreement. The Aggregate Completion Agreement will list options the Customer must choose to clarify their commitment to remain in the ATSS. The only action required on OASIS is to WITHDRAW the request or leave the request in STUDY mode.

The Transmission Provider must receive an unconditional and irrevocable letter of credit in the amount of the total allocated E&C costs assigned to the Customer. This letter of credit is not required for those facilities that are fully base plan funded. The amount of the letter of credit will be adjusted down on an annual basis to reflect cost recovery based on revenue allocation. The Transmission Provider will issue notifications to construct Network Upgrades to the constructing Transmission Owner after filing of necessary service agreements at FERC.

# Appendix A

#### PSS/E CHOICES IN RUNNING LOAD FLOW PROGRAM AND ACCC

#### **BASE CASE SETTINGS:**

• Solutions: Fixed slope decoupled Newton-Raphson solution

(FDNS)

Tap adjustment: Stepping

Area Interchange Control: Tie lines and loads
 Var limits: Apply immediately

• Solution Options:

X Phase shift adjustment

Flat start

\_ Lock DC taps

Lock switched shunts

#### **ACCC CASE SETTINGS:**

• Solutions: AC contingency checking (ACCC)

MW mismatch tolerance: 0.5
System intact rating: Rate A
Contingency case rating: Rate B
Percent of rating: 100
Output code: Summary

Min flow change in overload report: 3mw
Excld cases w/ no overloads from report: YES
Exclude interfaces from report: NO
Perform voltage limit check: YES
Elements in available capacity table: 60000
Cutoff threshold for available capacity 99999.0

table:

Min. contng. Case Vltg chng for report: 0.02
 Sorted output: None

Newton Solution:

• Tap adjustment: Stepping

Area interchange control:
 Tie lines and loads (Disabled for generator

outages)

• Var limits: Apply immediately

• Solution options:  $\underline{X}$  Phase shift adjustment

\_ Flat start

\_ Lock DC taps

\_\_Lock switched shunts

**Table 1** - Long-Term Transmission Service Requests Included in Aggregate Facility Study

Customer	Study Number	Reservation	POR	POD	Requested Amount	Requested Start Date	Requested Stop Date	Deferred Start Date without interim redispatch (ACA Parameter 3)	Deferred Stop Date without interim redispatch	Start Date with interim redispatch	Stop Date with interim redispatch	Minimum Allocated ATC (MW) within reservation period	Season of Minimum Allocated ATC within reservation period
AECC	2012-AG1-038	76585985	WR	CSWS	51	10/1/2012	10/1/2017	6/1/2015	6/1/2020	5/1/2014	5/1/2019	34	13SP
AECC	2012-AG1-040	76586012	WR	OKGE	51	7/1/2015	7/1/2020	6/1/2015	6/1/2020	7/1/2015	7/1/2020	34	23SP
AEPM	2012-AG1-033	76584399	CSWS	CSWS	250	1/1/2016	1/1/2021	1/1/2016	1/1/2021	1/1/2016	1/1/2021	148	23SP
AEPM	2012-AG1-034	76584402	CSWS	CSWS	250	1/1/2016	1/1/2021	1/1/2016	1/1/2021	1/1/2016	1/1/2021	148	23SP
AEPM	2012-AG1-036	76584451	WR	CSWS	78	10/1/2012	1/1/2032	6/1/2018	9/1/2037	5/1/2014	8/1/2033	0	13SP
AEPM	2012-AG1-037	76584464	SPS	CSWS	80	10/1/2012	1/1/2032	6/1/2017	9/1/2036	5/1/2014	8/1/2033	0	13SP
AEPM	2012-AG1-042	76586559	OKGE	CSWS	101	10/1/2012	12/31/2032	5/1/2014	7/1/2034	5/1/2014	7/1/2034	60	13SP
AEPM	2012-AG1-044	76586582	OKGE	CSWS	53	10/1/2012	12/31/2032	5/1/2014	7/1/2034	5/1/2014	7/1/2034	31	13SP
AEPM	2012-AG1-046	76586592	OKGE	CSWS	48	10/1/2012	12/31/2032	5/1/2014	7/1/2034	5/1/2014	7/1/2034	28	13SP
CHAN	2012-AG1-028	76583997	KACY	WR	3	1/1/2014	1/1/2019	5/1/2014	5/1/2019	5/1/2014	5/1/2019	3	14SP
CHAN	2012-AG1-029	76583999	KCPL	WR	45	1/1/2014	1/1/2019	5/1/2014	5/1/2019	5/1/2014	5/1/2019	45	14SP
CHAN	2012-AG1-031	76584004	SPA	WR	1	1/1/2014	1/1/2019	5/1/2014	5/1/2019	5/1/2014	5/1/2019	1	14SP
CHAN	2012-AG1-032	76584010	WR	WR	121	1/1/2014	1/1/2019	5/1/2014	5/1/2019	5/1/2014	5/1/2019	121	14SP
CHAN	2012-AG1-050	76586685	NPPD	WR	2	1/1/2014	1/1/2019	5/1/2014	5/1/2019	5/1/2014	5/1/2019	0	14SP
CHAN	2012-AG1-052	76583977	WR	WR	115	1/1/2014	1/1/2019	5/1/2014	5/1/2019	5/1/2014	5/1/2019	115	14SP
CHAN	2012-AG1-053	76583984	GRDA	WR	2	1/1/2014	1/1/2019	5/1/2014	5/1/2019	5/1/2014	5/1/2019	2	14SP
CRGL	2012-AG1-001	76300099	CSWS	ERCOTN	207	1/1/2014	1/1/2024	6/1/2016	6/1/2026	5/1/2014	5/1/2024	0	14SP
CRGL	2012-AG1-025	76583812	WPEK	EES	200	1/1/2014	1/1/2024	1/1/2015	1/1/2025	1/1/2015	1/1/2025	0	14SP
CRGL	2012-AG1-026	76583814	WPEK	EES	200	1/1/2014	1/1/2024	1/1/2015	1/1/2025	1/1/2015	1/1/2025	0	14SP
KMEA	2012-AG1-012	76580367	NPPD	WR	1	5/1/2013	4/30/2025	5/1/2014	5/1/2026	5/1/2014	5/1/2026	1	13SP
KMEA	2012-AG1-013	76580375	GRDA	WR	3	5/1/2013	5/1/2026	5/1/2014	5/1/2027	5/1/2014	5/1/2027	3	13SP
KMEA	2012-AG1-014	76580381	KACY	WR	4	10/1/2013	6/1/2022	5/1/2014	1/1/2023	5/1/2014	1/1/2023	4	14SP
KMEA	2012-AG1-015	76580392	SPA	WR	1	5/1/2013	1/1/2019	5/1/2014	1/1/2020	5/1/2014	1/1/2020	1	13SP
KMEA	2012-AG1-017	76580515	SPA	WR	1	1/1/2014	1/1/2019	5/1/2014	5/1/2019	5/1/2014	5/1/2019	1	14SP
KMEA	2012-AG1-018	76580552	NPPD	WR	1	1/1/2014	5/1/2025	5/1/2014	9/1/2025	5/1/2014	9/1/2025	1	14SP
KMEA	2012-AG1-019	76582326	WR	WR	41	5/1/2013	5/1/2026	5/1/2014	5/1/2027	5/1/2014	5/1/2027	41	13SP
KMEA	2012-AG1-022	76583607	WR	WR	21	1/1/2014	5/1/2026	5/1/2014	9/1/2026	5/1/2014	9/1/2026	21	14SP
KMEA	2012-AG1-023	76583617	GRDA	WR	5	1/1/2014	5/1/2026	5/1/2014	9/1/2026	5/1/2014	9/1/2026	5	14SP
KMEA	2012-AG1-048	76586675	KCPL	WR	15	6/1/2013	6/1/2023	6/1/2018	6/1/2028	5/1/2014	5/1/2024	0	13SP
KMEA	2012-AG1-049	76586679	WR	WR	15	6/1/2013	6/1/2023	5/1/2014	5/1/2024	5/1/2014	5/1/2024	15	13SP
KMEA	2012-AG1-051	76586961	NPPD	WR	1	6/1/2013	5/1/2025	5/1/2014	4/1/2026	5/1/2014	4/1/2026	0	13SP
OGE	2012-AG1-008	76571379	OKGE	OKGE	60	12/19/2012	12/19/2032	6/1/2015	6/1/2035	5/1/2014	5/1/2034	0	13SP
PSCM	2012-AG1-021	76582673	SPS	LAM345	208	3/1/2013	3/1/2018	1/1/2015	1/1/2020	Note 4	Note 4	0	13SP
WFEC	2012-AG1-004	76548687	CSWS	WFEC	160	6/1/2014	12/31/2035	6/1/2014	12/1/2035	6/1/2014	12/1/2035	160	14SP
WFEC	2012-AG1-005	76548692	CSWS	WFEC	90	6/1/2017	12/31/2035	6/1/2017	12/1/2035	6/1/2017	12/1/2035	90	23SP
WFEC	2012-AG1-006	76548702	CSWS	WFEC	30	6/1/2019	12/31/2035	6/1/2019	12/1/2035	6/1/2019	12/1/2035	30	23SP

Note 1: Start and Stop Dates with interim redispatch are determined based on customers choosing option to pursue redispatch to start service at Requested Start and Stop Dates or earliest date possible.

Note 2: Start dates with and without redispatch are based on the assumed completion dates of previous Aggregate Transmission Service Studies currently being conducted. Actual start dates may differ from the potential start dates upon completion of the previous studies.

Note 3: Request is unable to be deferred due to fixed stop dates.

**Note 4**: Transmission customer did not select "remain in the study using interim redispatch" option.

 Table 2 - Total Revenue Requirements Associated with Long-Term Transmission Service Requests

Customer	Study Number	Reservation	Engineering and Construction Cost of Upgrades Allocated to Customer for Revenue Requirements	<sup>1</sup> Letter of Credit Amount Required (ACA Parameter 5)	<sup>2</sup> Potential Base Plan Engineering and Construction Funding Allowable	Notes	<sup>4</sup> Additional Engineering and Construction Cost for 3rd Party Upgrades (ACA Parameter 2)	<sup>3 5</sup> Total Revenue Requirements for Assigned Upgrades Over Term of Reservation WITH Potential Base Plan Funding Allocation	Point-to-Point Base Rate Over Reservation Period	<sup>4</sup> Total Cost of Reservation Assignable to Customer Contingent Upon Base Plan Funding	Directly Assigned Upgrade Cost (DAUC) (ACA Parameter 1)
AECC	2012-AG1-038	76585985	\$ -	\$ -	\$ -		\$ 15,336	\$ -	\$ -	Schedule 9 & 11 Charges	
AECC	2012-AG1-040	76586012	\$ -	\$ -	\$ -		\$ -	\$ -	\$ -	Schedule 9 & 11 Charges	
AEPM	2012-AG1-033	76584399	\$ -	\$ -	\$ -		\$ 3,260		\$ -	Schedule 9 & 11 Charges	
AEPM	2012-AG1-034	76584402	\$ -	\$ -	\$ -		\$ 3,179		\$ -	Schedule 9 & 11 Charges	
AEPM	2012-AG1-036	7 000 1 10 2	\$ -	\$ -	\$ -		\$ 915	1	\$ .	Schedule 9 & 11 Charges	
AEPM	2012-AG1-037	76584464	\$ -	\$ -	\$ -		\$ 943		\$ -	Schedule 9 & 11 Charges	
AEPM	2012-AG1-042		\$ -	\$ -	\$ -		\$ 1,214		\$ .	Schedule 9 & 11 Charges	
AEPM	2012-AG1-044	76586582	\$ -	\$ -	\$ -		\$ 637		\$ .	Schedule 9 & 11 Charges	
AEPM	2012-AG1-046		\$ -	\$ -	\$ -		\$ 577	\$ -	\$	Schedule 9 & 11 Charges	
CHAN	2012-AG1-028	76583997	\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
CHAN	2012-AG1-029	76583999	\$ -	\$ -	\$ -		\$ -	\$ -	\$	Schedule 9 & 11 Charges	
CHAN	2012-AG1-031	76584004	\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
CHAN	2012-AG1-032	76584010	\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
CHAN	2012-AG1-050	76586685	\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
CHAN	2012-AG1-052	76583977	\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
CHAN	2012-AG1-053	, 656556 1	\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
CRGL	2012-AG1-001	, 6566655	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 47,113,531		
CRGL	2012-AG1-025	76583812	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 30,720,000		
CRGL	2012-AG1-026	76583814	\$ -	\$ -	\$ -		\$ -	\$ -	\$ 30,720,000		
KMEA	2012-AG1-012		\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
KMEA	2012-AG1-013	76580375		\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
KMEA	2012-AG1-014		\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
KMEA	2012-AG1-015	76580392	<u>\$</u> -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
KMEA	2012-AG1-017	76580515	•	\$ -	\$ -		\$ -	-	\$ -	Schedule 9 & 11 Charges	
KMEA	2012-AG1-018		\$ -	\$ -	\$ -		\$ -	\$ -	\$ ·	Schedule 9 & 11 Charges	
KMEA	2012-AG1-019		\$ -	\$ -	\$ -		\$ -	\$ -	\$ .	Schedule 9 & 11 Charges	
KMEA	2012-AG1-022		\$ -	\$ -	\$ -		\$ -	> -	\$ .	Schedule 9 & 11 Charges	
KMEA	2012-AG1-023 2012-AG1-048	76583617	<del>-</del>	\$ - \$ -	\$ - \$ -		\$ -	<del>-</del> -	٠ د	Schedule 9 & 11 Charges	
KMEA KMEA	2012-AG1-048 2012-AG1-049	76586675 76586679	\$ -	\$ -	\$ -		\$ -	<u>-</u> د	\$ -	Schedule 9 & 11 Charges Schedule 9 & 11 Charges	
KMEA	2012-AG1-049 2012-AG1-051		\$ - \$	\$ -	\$ -		<u> </u>	<u>-</u> د	د	Schedule 9 & 11 Charges Schedule 9 & 11 Charges	
OGE	2012-AG1-051 2012-AG1-008		\$ 1,131,409	'	\$ 1,131,409		\$ -	<u>-</u> د	\$ .	Schedule 9 & 11 Charges Schedule 9 & 11 Charges	
PSCM	2012-AG1-008 2012-AG1-021		\$ 1,131,409	٠ -	\$ 1,131,409		\$ -	- -	\$ 23,137,920		
WFEC	2012-AG1-021 2012-AG1-004		\$ - \$ -	\$ -	\$ -		\$ - \$ -	- -	ر کارنگار خ	Schedule 9 & 11 Charges	
WFEC	2012-AG1-004 2012-AG1-005	76548692	<del>,</del>	\$ -	\$ -		<u>-</u> د د	<u>-</u> د د	\$ .	Schedule 9 & 11 Charges  Schedule 9 & 11 Charges	
WFEC	2012-AG1-003		\$ -	\$ -	\$ -		\$ -	¢ -	ς .	Schedule 9 & 11 Charges Schedule 9 & 11 Charges	
Grand Total	2012-A01-000	70340702	\$1,131,409	т	\$1,131,409		\$26,061	\$0	, ,	Schedule 9 & 11 charges	<del>-</del>

**Table 2** - Total Revenue Requirements Associated with Long-Term Transmission Service Requests

Customer Study Number Reservation Upgrades Allocated to Customer for Revenue Requirements	<sup>1</sup> Letter of Credit Amount Required (ACA Parameter 5) <sup>2</sup> Potential Base Plan Engineering and Construction Funding Allowable	<sup>4</sup> Additional Engineering and Construction Cost for 3rd Party Upgrades (ACA Parameter 2)  3 5 Total Revenue Requirements for Assigned Upgrades Over Term of Reservation WITH Potential Base Plan Funding Allocation  Point-to-Point Base Rate Over Reservation Period	<sup>4</sup> Total Cost of Reservation Assignable to Customer Contingent Upon Base Plan Funding  Directly Assigned Upgrade Cost (DAUC) (ACA Parameter 1)
---	--	---	--

**Note 1:** Letter of Credit required for financial security for transmission owner for network upgrades is determined by allocated engineering and construction costs for upgrades when network customer is the transmission owner less the E & C allocation of expedited projects. Letter of Credit is required for upgrades assigned to PTP requests. The amount of the letter of credit will be adjusted down on an annual basis to reflect cost recovery based on revenue allocation. This letter of credit is not required for those facilities that are fully base plan funded. The Letter Of Credit Amount listed is based on meeting OATT Attachment J requirements for base plan funding.

Note 2: If potential base plan funding is applicable, this value is the lesser of the Engineering and Construction costs of assignable upgrades or the value of base plan funding calculated pursuant to Attachment J, Section III B criteria. Allocation of base plan funding is contingent upon verification of customer agreements meeting Attachment J, Section II B criteria. Not applicable if Point-to-Point base rate exceeds revenue requirements.

Note 3: Revenue Requirements (RR) are based upon deferred end dates if applicable. Deferred dates are based upon customer's choice to pursue redispatch. Achievable Base Plan Avoided RR in the case of a Base Plan upgrade being displaced or deferred by an earlier in service date for a Requested Upgrade shall be determined per Attachment J, Section VII.C methodology. Assumption of a 40 year service life is utilized for Base Plan funded projects. A present worth analysis of RR on a common year basis between the Base Plan and Requested Upgrades was performed to determine avoided Base Plan RR due to the displacement or deferral of the Base Plan upgrade by the Requested Upgrade. The incremental increase in present worth of a Requested Upgrade on a common year basis as a Base Plan upgrade is assigned to the transmission requests impacting the upgrade based on the displacement or deferral. If the displacement analysis results in lower RR due to the shorter amortization period of the requested upgrade when compared to a base plan amortization period, then no direct assignment of the upgrade cost is made due to the displacement to an earlier start date.

**Note 4:** For Point-to-Point requests, total cost is based on the higher of the base rate or assigned upgrade revenue requirements. For Network requests, the total cost is based on the assigned upgrade revenue requirement. Allocation of base plan funding will be determined after verification of designated resource meeting Attachment J, Section II B Criteria. Additionally E & C of 3rd Party upgrades is assignable to Customer. This includes prepayments required for any SWPA upgrades. Revenue requirements for 3rd Party facilities are not calculated. Total cost to customer is based on assumption of Revenue Requirements with confirmation of base plan funding. Customer is responsible for negotiating redispatch costs if applicable. Customer is also responsible to pay credits for previously assigned upgrades that are impacted by their request. Credits can be paid from base plan funding if applicable.

Note 5: RR with base plan funding may increase or decrease even if no base plan funding is applicable to a particular request that shares the upgrade is now full base plan funded resulting in a different amortization period for the upgrade and thus different RR.

				Requested	Requested Start			•	Potential Base Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AECC	76585985	WR	CSWS	51	10/1/2012	10/1/2017	6/1/2015	6/1/2020	\$ -	\$ -	\$ -	\$ -
									\$ -	\$ -	\$ -	\$ -

				Redispatch		, ,	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN	EOC	Date	Available	Funding for Wind	for Wind	Cost	Total E & C Cost	Requirements
76585985 None					\$ -	\$ -	\$ -	\$ -	\$ -
				Total	\$ -	\$ -	\$ -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76585985	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1	6/1/2014	6/1/2015		Yes

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76585985	Viola - Clearwater 138kV Ckt1	10/1/2014	6/1/2018		
	Viola - Gill 138kV Ckt1	10/1/2014	6/1/2018		
	Viola 345/138kV Transformer Ckt 1	10/1/2014	6/1/2018		

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76585985	ASHDOWN REC (MILLWOOD) - OKAY 138KV CKT 1	7/1/2012	7/1/2012		
	ASHDOWN REC (MILLWOOD) - PATTERSON 138KV CKT 1	7/1/2012	7/1/2012		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	MANDEVILTP4 - SE TEXARKANA 138KV CKT 1	7/1/2012	7/1/2012		
	MANDEVILTP4 - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	MCNAB REC - TURK 115KV CKT 1	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	OKAY - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	SUGAR HILL - TURK 138KV CKT 1	7/1/2012	7/1/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

				Earliest Start	Redispatch	*Allocated	J & B C	1	
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		*Total E &	C Cost
76585985	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	6/1/2018	6/1/2019			\$	15,336	\$	26,061
					Total	\$	15,336	\$	26,061

<sup>\*</sup>Estimated cost allocation as a percentage of total cost is shown for third-party limitations when costs have not yet been established by the third-party.

 $<sup>{}^{*}\</sup>text{Credits}$  may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	<b>Potential Base</b>			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AECC	76586012	WR	OKGE	5:	1 7/1/201	7/1/202	O .		\$	- \$ -	\$ -	\$ -
									\$	- \$ -	\$ -	\$ -

			Earliest Start	Redispatch	Base Plan	Directly Assigned	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN	EOC	Date	Available	Funding for Wind	for Wind	Cost	Total E & C Cost	Requirements
76586012 None					\$ -	\$ -	\$ -	\$ -	\$ -
				Total	\$ -	\$ -	\$ -	\$ -	\$ -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*\*</sup>Reservation 76586012 studied as resevation 76585985

Customer	Reservation	POR		1.	Requested Start Date	Requested Stop	Deferred Start Date Without Redispatch	Date Without	Potential Base Plan Funding Allowable		Allocated E & C	Total Revenue Requirements
AEPM	76584399	CSWS	CSWS	250	1/1/2016		•		\$ -	\$ -	\$	- \$ -
									\$ -	\$ -	\$	- \$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76584399	None					\$ -	\$ -	\$
				·	Total	ς -	ς -	ς .

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584399	CHAMBER SPRINGS - FARMINGTON AFCC 161KV CKT 1	6/1/2014	6/1/2015		

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584399	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		

				Earliest Start	Redispatch	*Allocated	E & C		
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		*Total E & (	C Cost
76584399	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	6/1/2018	6/1/2019			\$	3,260	\$	26,061
					Total	\$	3,260	\$	26,061

<sup>\*</sup>Estimated cost allocation as a percentage of total cost is shown for third-party limitations when costs have not yet been established by the third-party.

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AEPM	76584402	CSWS	CSWS	250	1/1/2016	1/1/2021			\$ -	\$ -	\$ -	\$ -
<u> </u>			_						\$ -	\$ -	\$ -	Ś -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76584402	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584402	CHAMBER SPRINGS - FARMINGTON AFCC 161KV CKT 1	6/1/2014	6/1/2015		

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584402	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		

				Earliest Start	Redispatch	*Allocated E	& C	
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		*Total E & C Cost
76584402	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	6/1/2018	6/1/2019			\$ 3,3	179	\$ 26,061
					Total	\$ 3,:	179	\$ 26,061

<sup>\*</sup>Estimated cost allocation as a percentage of total cost is shown for third-party limitations when costs have not yet been established by the third-party.

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

								Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AEPM	76584451	WR	CSWS	78	10/1/2012	1/1/2032	6/1/2018	9/1/2037	\$ -	\$ -	\$ -	\$
									\$ -	\$ -	\$ -	<b>\$</b> .

			Earliest Start	Redispatch	Base Plan	Directly Assigned	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN	EOC		·	Funding for Wind		Cost		Requirements
76584451 None					\$ -	\$ -	\$ -	\$ -	\$ -
	•			Total	\$ -	\$ -	\$ -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584451	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1	6/1/2014	6/1/2015		
	IATAN - NASHUA 345KV CKT 1	6/1/2014	6/1/2015		Yes

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584451	Viola - Clearwater 138kV Ckt1	10/1/2014	6/1/2018		Yes
	Viola - Gill 138kV Ckt1	10/1/2014	6/1/2018		Yes
	Viola 345/138kV Transformer Ckt 1	10/1/2014	6/1/2018		Yes

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584451	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

				Earliest Start	Redispatch	*Allocated E & C	
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	*Total E & C Cost
76584451	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	6/1/2018	6/1/2019			\$ 915	\$ 26,061
					Total	\$ 915	\$ 26,061

<sup>\*</sup>Estimated cost allocation as a percentage of total cost is shown for third-party limitations when costs have not yet been established by the third-party.

 $<sup>\</sup>hbox{$^*$Credits may be required for applicable generation interconnection network upgrades.}$ 

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AEPM	76584464	SPS	CSWS	80	10/1/2012	1/1/2032	6/1/201	7 9/1/2036	\$ -	\$ -	\$	- \$ -
									\$ -	\$ -	\$	- \$ -

			Earliest Start	Redispatch	Base Plan	Directly Assigned	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN	EOC	Date	Available	Funding for Wind	for Wind	Cost	Total E & C Cost	Requirements
76584464 None					\$ -	\$ -	\$ -	\$ -	\$ -
•	•	•	•	Total	\$ -	\$ -	\$ -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584464	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1	6/1/2014	6/1/2015		
	Line - Clark County - Thistle 345 kV dbl Ckt	5/1/2014	1/1/2015		Yes
	Line - Hitchland - Woodward 345 kV dbl Ckt OKGE	5/1/2014	7/1/2014		Yes
	Line - Hitchland - Woodward 345 kV dbl Ckt SPS	5/1/2014	7/1/2014		Yes
	Line - Spearville - Clark County 345 kV dbl Ckt	5/1/2014	1/1/2015		Yes
	Line - Thistle - Wichita 345 kV dbl Ckt PW	5/1/2014	1/1/2015		Yes
	Line - Thistle - Wichita 345 kV dbl Ckt WERE	5/1/2014	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	5/1/2014	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt PW	5/1/2014	1/1/2015		Yes
	Line - Tuco - Woodward 345 kV line OKGE	5/1/2014	6/1/2014		
	Line - Tuco - Woodward 345 kV line SPS	5/1/2014	6/1/2014		
	XFR - Thistle 345/138 kV	5/1/2014	1/1/2015		Yes

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584464	BUSHLAND INTERCHANGE - DEAF SMITH COUNTY INTERCHANGE 230KV CKT 1	10/1/2014	6/1/2016		Yes
	CANYON EAST SUB - RANDALL COUNTY INTERCHANGE 115KV CKT 1	6/1/2014	6/1/2017		Yes

Construction Pending - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584464	CANYON EAST SUB - CANYON WEST SUB 115KV CKT 1	5/1/2014	6/1/2017		Yes

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584464	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	6/1/2015	6/1/2015		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - IODINE 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

111111111111111111111111111111111111111	Tarty Emilie	idons.							
					Earliest Start	Redispatch	*Allocated E 8	ķ C	
Reser	vation	Upgrade Name	DUN	EOC	Date	Available	Cost		*Total E & C Cost
	76584464	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	6/1/2018	6/1/2019			\$ 9	943	\$ 26,061
						Total	\$ 9	943	\$ 26,061

<sup>\*</sup>Estimated cost allocation as a percentage of total cost is shown for third-party limitations when costs have not yet been established by the third-party.

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

				Paguastad	Requested Start			•	Potential Base Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR		_		•						Requirements
AEPM	76586559	OKGE	CSWS	101	10/1/2012	12/31/2032	5/1/2014	7/1/2034	\$ -	\$ -	\$ -	\$
									\$ -	\$ -	\$ -	\$

		Earliest Start	Redispatch	Base Plan	Directly Assigned	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN		*	Funding for Wind	, ,	Cost		Requirements
76586559 None				\$ -	\$ -	\$ -	\$ -	\$ -
	Total	\$ -	\$ -	\$ -	\$ -	\$ -		

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586559	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1	6/1/2014	6/1/2015		

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586559	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

				Earliest Start	Redispatch	*Allocated	E & C		
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost		*Total E & C	2 Cost
76586559	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	6/1/2018	6/1/2019			\$	1,214	\$	26,061
					Total	\$	1,214	\$ 7	26,061

<sup>\*</sup>Estimated cost allocation as a percentage of total cost is shown for third-party limitations when costs have not yet been established by the third-party.

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

				Requested	Requested Start	Requested Stop		•	Potential Base Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AEPM	76586582	OKGE	CSWS	53	10/1/2012	12/31/2032	5/1/2014	7/1/2034	\$ -	\$ -	\$ -	\$
									\$ -	\$ -	\$ -	\$

				Redispatch		, ,	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN	EOC	Date	Available	Funding for Wind	for Wind	Cost	Total E & C Cost	Requirements
76586582 None					\$ -	\$ -	\$ -	\$ -	\$ -
	Total	\$ -	\$ -	\$ -	\$ -	\$ -			

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586582	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1	6/1/2014	6/1/2015		

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586582	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

				Earliest Start	Redispatch	*Allocated E &	0	
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	*Tc	otal E & C Cost
76586582	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	6/1/2018	6/1/2019			\$ 63	7 \$	26,061
					Total	\$ 63	7 \$	26,061

<sup>\*</sup>Estimated cost allocation as a percentage of total cost is shown for third-party limitations when costs have not yet been established by the third-party.

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

					Defe			Deferred Start Deferred Stop		Potential Base			
				Requested	Requ	uested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	9	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
AEPM	76586592	OKGE	CSWS		48	10/1/2012	12/31/2032	5/1/2014	7/1/2034	\$	- \$ -	\$ -	\$ -
										\$	- \$ -	\$ -	\$ -

			Earliest Start	Redispatch	Base Plan	Directly Assigned	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN	EOC	Date	Available	Funding for Wind	for Wind	Cost	Total E & C Cost	Requirements
76586592 None					\$ -	\$ -	\$ -	\$ -	\$ -
				Total	\$ -	\$ -	\$ -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

							Earliest Start	Redispatch
Reservation	Upgrade Name				DUN	EOC	Date	Available
76586592	CHAMBER SPRINGS - FARMING	GTON AECC 161	1KV CKT 1		6/1/2014	6/1/2015		

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586592	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

				Earliest Start	Redispatch	*Allocated E & C	
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	*Total E & C Cost
76586592	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	6/1/2018	6/1/2019			\$ 577	\$ 26,061
					Total	\$ 577	\$ 26.061

<sup>\*</sup>Estimated cost allocation as a percentage of total cost is shown for third-party limitations when costs have not yet been established by the third-party.

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

									Deferred Start	Deferred Stop	<b>Potential Base</b>				
					Requested	Reque	ested Start	Requested St	op Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>	
Customer	Reservation		POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements	
CHAN		76583997	KACY	WR		3	1/1/2014	1/1/	2019 5/1/201	5/1/2019	\$	- \$ -	\$ -	\$	-
	_				·	-				_	¢	_ ¢	Ċ -	Ċ	

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76583997	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

				Requested	Requested Start		Deferred Start Date Without		Potential Base Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
CHAN	76583999	KCPL	WR	45	1/1/2014	1/1/2019	5/1/2014	5/1/2019	\$ -	\$ -	\$	- \$ -
									\$ -	\$ -	\$	- \$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76583999	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76583999	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

								Deferred Start	•	Potential Base			
				Requested	Requ	ested Start	Requested Sto	p Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	<b>Base Rate</b>	Cost	Requirements
CHAN	76584004	SPA	WR		1	1/1/2014	1/1/2	5/1/2014	5/1/2019	\$	- \$ -	\$ -	\$
		<u> </u>	·	<u> </u>				_		ς	- ¢ -	ς -	ζ

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76584004	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

								Deferred Start	Deferred Stop	Potential Base			
				Requested	Requ	ested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer Re	eservation F	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
CHAN	76584010 V	WR	WR		121	1/1/2014	1/1/20	19 5/1/2014	5/1/2019	\$	- \$ -	\$ -	\$
							_			\$	- \$ -	\$ -	\$

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76584010	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76584010	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	DEARING 138KV Capacitor	6/1/2012	6/1/2012		
	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	6/1/2013	6/1/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

Contains	D	DOD.		l _ '	Requested Start	Requested Stop		Date Without	•			Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
CHAN	76586685	NPPD	WR	2	1/1/2014	1/1/2019	5/1/2014	5/1/2019	\$ -	\$ -	\$	- \$ -
•		_		<u> </u>	·	<u> </u>	_	_	č	خ ا	۲	<b>č</b>

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76586685	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586685	Butler - Weaver 138kV CKT 1 #2	6/1/2015	6/1/2018		

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586685	ALBION - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	DEARING 138KV Capacitor	6/1/2012	6/1/2012		
	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	6/1/2013	6/1/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NELIGH - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

				Requested	Requested Start	Requested Stop	Deferred Start Date Without	•	Potential Base Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
CHAN	76583977	WR	WR	115	1/1/2014	1/1/2019	5/1/2014	5/1/2019	\$ -	\$ -	\$	- \$ -
									ς -	ς -	ς	- Ś -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76583977	None					\$ -	\$ -	\$ -
					Total	Ś -	\$ -	\$ -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

									Deferred Start	Deferred Stop	Potential Base				
					Requested	Reques	sted Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>	
Customer	Reservation		POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements	
CHAN		76583984	GRDA	WR		2	1/1/2014	1/1/20	19 5/1/2014	5/1/2019	\$	- \$ -	\$ -	\$	-
											Ċ	Ċ	Ċ	خ	

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76583984	None					\$ -	\$ -	\$ -
					Total	Ś -	\$ -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

				Requested	Requested Start	Requested Stop	Date Without	Date Without	_	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
CRGL	76300099	CSWS	ERCOTN	207	1/1/2014	1/1/2024	6/1/2016	6/1/2026	\$ -	\$ 47,113,531	\$	- \$ -
									\$ -	\$ 47,113,531	\$	- \$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76300099	None					\$ -	\$ -	\$ -
		_			Total	\$ -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76300099	Line - Clark County - Thistle 345 kV dbl Ckt	5/1/2014	1/1/2015		Yes
	Line - Hitchland - Woodward 345 kV dbl Ckt OKGE	5/1/2014	7/1/2014		
	Line - Hitchland - Woodward 345 kV dbl Ckt SPS	5/1/2014	7/1/2014		
	Line - Spearville - Clark County 345 kV dbl Ckt	5/1/2014	1/1/2015		Yes
	Line - Thistle - Wichita 345 kV dbl Ckt PW	5/1/2014	1/1/2015		Yes
	Line - Thistle - Wichita 345 kV dbl Ckt WERE	5/1/2014	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	5/1/2014	1/1/2015		Yes
	Line - Thistle - Woodward 345 kV dbl Ckt PW	5/1/2014	1/1/2015		Yes
	Line - Tuco - Woodward 345 kV line OKGE	5/1/2014	6/1/2014		
	Line - Tuco - Woodward 345 kV line SPS	5/1/2014	6/1/2014		
	XFR - Thistle 345/138 kV	5/1/2014	1/1/2015		Yes

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76300099	BUSHLAND INTERCHANGE - DEAF SMITH COUNTY INTERCHANGE 230KV CKT 1	10/1/2014	6/1/2016		Yes

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76300099	BANN - RED SPRINGS REC 138KV CKT 1	7/1/2012	7/1/2012		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	1/1/2012	1/1/2012		
	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	1/1/2012	1/1/2012		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>The North DC Tie is derated to 210mw indefinately.

<sup>\*</sup>The NORTH DC tie is scheduled for an outage beginning 12/1/2013 until 3/31/2014 to refurbish the facility.

<sup>\*198</sup> MW of available ERCOT North to South capacity without consideration of prior queued STUDY requests in active Aggregate Transmission Service Studies.

<sup>\*</sup>Available capacity will be allocated on a first come first served basis in accordance with Attachment Z1 III.b. of SPP OATT.

							Deferred S	tart	Deferred Stop	Potential Base				
				Requested	Requested S	tart Request	ed Stop Date With	out	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>	
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatcl	1	Redispatch	Allowable	Base Rate	Cost	Requirements	
CRGL	76583812	WPEK	K EES	2	00 1/1	2014	1/1/2024	1/1/2015	1/1/2025	\$ -	\$ 30,720,000	\$ -	\$	-
·				_						\$ -	\$ 30,720,000	\$ -	\$	

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76583812	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76583812	Line - Clark County - Thistle 345 kV dbl Ckt	5/1/2014	1/1/2015		No
	Line - Hitchland - Woodward 345 kV dbl Ckt OKGE	5/1/2014	7/1/2014		
	Line - Hitchland - Woodward 345 kV dbl Ckt SPS	5/1/2014	7/1/2014		
	Line - Spearville - Clark County 345 kV dbl Ckt	5/1/2014	1/1/2015		No
	Line - Thistle - Wichita 345 kV dbl Ckt PW	5/1/2014	1/1/2015		No
	Line - Thistle - Wichita 345 kV dbl Ckt WERE	5/1/2014	1/1/2015		No
	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	5/1/2014	1/1/2015		No
	Line - Thistle - Woodward 345 kV dbl Ckt PW	5/1/2014	1/1/2015		No
	Line - Tuco - Woodward 345 kV line OKGE	5/1/2014	6/1/2014		
	Line - Tuco - Woodward 345 kV line SPS	5/1/2014	6/1/2014		
	XFR - Thistle 345/138 kV	5/1/2014	1/1/2015		No

Credits may be required for the following Network Upgrades in accordance with Attachment Z2 of the SPP OATT.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76583812	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Customer Study Number CRGL 2012-AG1-026

				Requested	Requested Start			•	Potential Base Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR			•				Allowable		Cost	Requirements
CRGL	76583814	WPEK	EES	200	1/1/2014	1/1/2024	1/1/2015	1/1/2025	\$ -	\$ 30,720,000	\$ -	\$
			_						\$ -	\$ 30,720,000	\$ -	Ś

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76583814	None					\$ -	\$ -	\$
					Total	ς -	ς -	\$

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76583814	Line - Clark County - Thistle 345 kV dbl Ckt	5/1/2014	1/1/2015		No
	Line - Hitchland - Woodward 345 kV dbl Ckt OKGE	5/1/2014	7/1/2014		
	Line - Hitchland - Woodward 345 kV dbl Ckt SPS	5/1/2014	7/1/2014		
	Line - Spearville - Clark County 345 kV dbl Ckt	5/1/2014	1/1/2015		No
	Line - Thistle - Wichita 345 kV dbl Ckt PW	5/1/2014	1/1/2015		No
	Line - Thistle - Wichita 345 kV dbl Ckt WERE	5/1/2014	1/1/2015		No
	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	5/1/2014	1/1/2015		No
	Line - Thistle - Woodward 345 kV dbl Ckt PW	5/1/2014	1/1/2015		No
	Line - Tuco - Woodward 345 kV line OKGE	5/1/2014	6/1/2014		
	Line - Tuco - Woodward 345 kV line SPS	5/1/2014	6/1/2014		
	XFR - Thistle 345/138 kV	5/1/2014	1/1/2015		No

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76583814	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

				l _ '	Requested Start	Requested Stop		Date Without	•			Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76580367	NPPD	WR	1	5/1/2013	4/30/2025	5/1/2014	5/1/2026	\$ -	\$ -	. \$	- \$ -
									\$ -	\$ -	. \$	- \$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76580367	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76580367	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	6/1/2013	6/1/2013		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

								Deferred Start	•	Potential Base			
				Requested	Requ	ested Start	<b>Requested Sto</b>	p Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76580375	GRDA	WR		3	5/1/2013	5/1/20	5/1/2014	5/1/2027	\$	- \$ -	\$ -	\$
										Ś	- Ś -	\$ -	Ś

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76580375	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

									Deferred Stop	Potential Base			
				Requested	Reque	ested Start	<b>Requested Stop</b>	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>
Customer	Reservation	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76580381	KACY	WR		4	10/1/2013	6/1/202	22 5/1/2014	1/1/2023	\$	- \$ -	\$ -	\$
										Ś	- Ś -	Ś -	Ś

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76580381	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

										Potential Base			
				Requested	Requ	ested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76580392	SPA	WR		1	5/1/2013	1/1/20	19 5/1/2014	1/1/2020	\$	- \$ -	\$ -	\$
										Ś	- Ś -	\$ -	Ś

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76580392	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

							Deferred Stop	Potential Base					
				Requested	Requ	ested Start	Requested Sto	p Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>
Customer Reservation		POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	<b>Base Rate</b>	Cost	Requirements
KMEA	76580515	SPA	WR		1	1/1/2014	1/1/20	)19 5/1/2014	5/1/2019	\$	- \$ -	\$ -	\$
										\$	- \$ -	\$ -	\$

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76580515	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76580515	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - RICE_CO 115KV CKT 1	10/1/2012	4/1/2013		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

									Deferred Start	Deferred Stop	Potential Base				
					Requested	Reque	sted Start	Requested Sto	p Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>	
Customer	Reservation		POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements	
KMEA		76580552	NPPD	WR		1	1/1/2014	5/1/2	5/1/2014	9/1/2025	\$	- \$ -	\$ -	\$	-
				<u> </u>				<u> </u>			٨	<b>A</b>	٨	٨	

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76580552	None					\$ -	\$ -	\$ -
		_	_		Total	ς -	ς -	ς -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76580552	ALBION - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	6/1/2013	6/1/2013		
	LYONS - RICE_CO 115KV CKT 1	10/1/2012	4/1/2013		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	NELIGH - PETERSBURG 115KV CKT 1	1/1/2013	1/1/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

				_ •	Requested Start	Requested Stop		Date Without	_			Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76582326	WR	WR	41	5/1/2013	5/1/2026	5/1/2014	5/1/2027	\$ -	\$ -	\$	- \$ -
									ς -	ς -	\$	- \$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76582326	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76582326	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	6/1/2013		
	BARBER - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	BARBER (BARBER 4) 138/115/2.72KV TRANSFORMER CKT 1	12/1/2009	6/1/2013		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	DEARING 138KV Capacitor	6/1/2012	6/1/2012		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	6/1/2013	6/1/2013		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - RICE_CO 115KV CKT 1	10/1/2012	4/1/2013		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
	SUB 110 - ORONOGO JCT SUB 167 - RIVERTON 161KV CKT 1	6/1/2011	6/1/2011		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

								Deferred Start	Deferred Stop	Potential Base			
				Requested	Requ	ested Start	<b>Requested Stop</b>	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>
Customer	Reservation	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76583607	WR	WR		21	1/1/2014	5/1/20	26 5/1/2014	9/1/2026	\$	- \$ -	\$ -	\$
										Ś	- Ś -	\$ -	Ś

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76583607	None					\$ -	\$ -	\$ -
					Total	\$ -	ς -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

								Deferred Start	Deferred Stop	Potential Base			
				Requested	Requ	ested Start	<b>Requested Sto</b>	p Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>
Customer	Reservation	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76583617	GRDA	WR		5	1/1/2014	5/1/20	5/1/2014	9/1/2026	\$	- \$ -	\$ -	\$
										Ś	- Ś -	Ś -	Ś

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76583617	None					\$ -	\$ -	\$ -
					Total	\$ -	ς -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

								Deferred Start	Deferred Stop	Potential Base			
				Requested	Requ	ested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76586675	KCPL	WR		15	6/1/2013	6/1/202	6/1/2018	6/1/2028	\$	- \$ -	\$ -	\$ -
										\$	- \$ -	\$ -	\$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76586675	None					\$ -	\$ -	\$ -
					Total	Ś -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586675	IATAN - NASHUA 345KV CKT 1	6/1/2014	6/1/2015		Yes

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586675	Cowskin - Westlink 69 kV Ckt 1	6/1/2014	12/1/2015		
	East Manhattan - Jeffrey Energy Center 230 kV Ckt 1	6/1/2019	6/1/2019		
	Gill 138/69 kV Transformer Ckt 3	6/1/2014	12/1/2015		Yes
	Hoover South - Tyler 69 kV Ckt 1	6/1/2014	6/1/2014		
	Tyler - Westlink 69 kV Ckt 1	6/1/2014	6/1/2015		
	Viola - Clearwater 138kV Ckt1	10/1/2014	6/1/2018		Yes
	Viola - Gill 138kV Ckt1	10/1/2014	6/1/2018		Yes
	Viola 345/138kV Transformer Ckt 1	10/1/2014	6/1/2018		Yes

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586675	ALEXANDER - PRATT 115KV CKT 1	12/1/2009	6/1/2013		
	BARBER - MEDICINE LODGE 115KV CKT 1	12/1/2009	6/1/2013		
	BARBER - SAWYER 115KV CKT 1	12/1/2009	6/1/2013		
	BARBER (BARBER 4) 138/115/2.72KV TRANSFORMER CKT 1	12/1/2009	6/1/2013		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	CIRCLE - RICE_CO 230KV CKT 1	10/1/2012	11/15/2012		
	CLIFTON - GREENLEAF 115KV CKT 1	6/1/2011	6/1/2013		
	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	12/1/2009	6/1/2013		
	FLATRDG3 138.00 - HARPER 138KV CKT 1	12/1/2009	6/1/2013		
	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	6/1/2013	6/1/2013		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	LYONS - RICE_CO 115KV CKT 1	10/1/2012	4/1/2013		
	LYONS - WHEATLAND 115KV CKT 1 #1	10/1/2012	7/15/2013		
	LYONS - WHEATLAND 115KV CKT 1 #2	10/1/2012	7/15/2013		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	RICE_CO 230/115KV TRANSFORMER CKT 1	10/1/2012	11/15/2012		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

								Deferred Start	Deferred Stop	Potential Base			
				Requested	Requ	ested Start	Requested Sto	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>
Customer	Reservation	POR	POD	Amount	Date		Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76586679	WR	WR		15	6/1/2013	6/1/20	23 5/1/2014	5/1/2024	\$	- \$ -	\$ -	\$
										ς	_	ς -	¢

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76586679	None					\$ -	\$ -	\$ -
					Total	ς -	ς -	ς -

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

								Deferred Start	Deferred Stop	Potential Base			
				Requested	Requ	uested Start	Requested S	Stop Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>
Customer	Reservation	POR	POD	Amount	Date	•	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
KMEA	76586961	NPPD	WR		1	6/1/2013	5/1	/2025 5/1/2014	4/1/2026	\$	- \$ -	\$ -	\$
										\$	- \$ -	\$ -	\$

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76586961	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76586961	Gill 138/69 kV Transformer Ckt 3	6/1/2014	12/1/2015		
	Viola - Clearwater 138kV Ckt1	10/1/2014	6/1/2018		
	Viola - Gill 138kV Ckt1	10/1/2014	6/1/2018		
	Viola 345/138kV Transformer Ckt 1	10/1/2014	6/1/2018		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

<sup>\*</sup>Underlying System Impacts and Upgrades have yet to be determined.

Customer Study Number
OGE 2012-AG1-008

							Deferred Start	Deferred Stop	Potential Base			
				Requested	Requested Start	Requested Stop	Date Without	Date Without	Plan Funding	Point-to-Point	Allocated E & C	<b>Total Revenue</b>
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
OGE	76571379	OKGE	OKGE	60	12/19/2012	12/19/2032	6/1/2015	6/1/2035	\$ 1,131,409	\$ -	\$ 1,131,40	9 \$ 3,118,195
									\$ 1,131,409	\$ -	\$ 1,131,40	9 \$ 3,118,195

			Earliest Start	Redispatch	Base Plan	Directly Assigned	Allocated E & C		Total Revenue
Reservation Upgrade Name	DUN	EOC	Date	Available	Funding for Wind	for Wind	Cost	Total E & C Cost	Requirements
76571379 Hefner - Tulsa 138kV CKT 1	6/1/201	9 6/1/2019			\$ 1,131,409	\$ -	\$ 1,131,409	\$ 1,131,409	\$ 3,118,195
				Total	\$ 1,131,409	\$ -	\$ 1,131,409	\$ 1,131,409	\$ 3,118,195

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76571379	DIVISION AVE - LAKESIDE 138KV CKT 1	6/1/2019	6/1/2019		

Construction Pending - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76571379	NORTHWEST 345/138/13.8KV TRANSFORMER CKT 3 Accelerated	6/1/2014	6/1/2015		Yes

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76571379	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

				Requested	Requested Start		Deferred Start Date Without	•	Potential Base Plan Funding	Point-to-Point	Allocated E & C	Total Revenue
Customer	Reservation	POR	POD	Amount	Date	Date	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements
PSCM	76582673	SPS	LAM345	208	3/1/2013	3/1/2018	1/1/2015	1/1/2020	\$ -	\$ 23,137,920	\$	- \$ -
									\$ -	\$ 23,137,920	\$	- \$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76582673	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

Expansion Plan - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76582673	Line - Clark County - Thistle 345 kV dbl Ckt	5/1/2014	1/1/2015		
	Line - Hitchland - Woodward 345 kV dbl Ckt OKGE	5/1/2014	7/1/2014		
	Line - Hitchland - Woodward 345 kV dbl Ckt SPS	5/1/2014	7/1/2014		
	Line - Spearville - Clark County 345 kV dbl Ckt	5/1/2014	1/1/2015		
	Line - Thistle - Wichita 345 kV dbl Ckt PW	5/1/2014	1/1/2015		
	Line - Thistle - Wichita 345 kV dbl Ckt WERE	5/1/2014	1/1/2015		
	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	5/1/2014	1/1/2015		
	Line - Thistle - Woodward 345 kV dbl Ckt PW	5/1/2014	1/1/2015		
	Line - Tuco - Woodward 345 kV line OKGE	5/1/2014	6/1/2014		
	Line - Tuco - Woodward 345 kV line SPS	5/1/2014	6/1/2014		
	XFR - Thistle 345/138 kV	5/1/2014	1/1/2015		

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76582673	CIMARRON RIVER TAP - KISMET 3 115.00 115KV CKT 1	10/1/2018	10/1/2018		
	CUDAHY - KISMET 3 115.00 115KV CKT 1	10/1/2018	10/1/2018		

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76582673	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	6/1/2015	6/1/2015		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	LACYGNE - WEST GARDNER 345KV CKT 1	6/1/2006	6/1/2006		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Customer Study Number WFEC 2012-AG1-004

Customer	Reservation	POR			Requested Start Date	Requested Stop	Deferred Start Date Without Redispatch	Date Without			Allocated E & C	Total Revenue Requirements
WFEC	76548687		WFEC	160	6/1/2014		•		\$ -	\$ -	\$	- \$ -
									\$ -	\$ -	\$	- \$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76548687	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76548687	BLUE CANYON - PARADISE 138KV CKT 1	6/1/2010	6/1/2013		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	7/1/2012	7/1/2012		
	NORTHWEST - TATONGA 345KV CKT 1	1/1/2010	1/1/2010		
	TATONGA - WOODWARD 345KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Customer Study Number WFEC 2012-AG1-005

					Requested	Requested	Start Re	equested Stop	Deferred Start Date Without	Deferred Stop Date Without	Potential Base Plan Funding	Point-to-Point	Allocated E & C	Total Revenue	
Customer	Reservation		POR	POD	Amount	Date	Da	ate	Redispatch	Redispatch	Allowable	Base Rate	Cost	Requirements	
WFEC	7	76548692	CSWS	WFEC	g	00 6/	1/2017	12/31/2035			\$ .	- \$ -	\$ -	\$	-
											\$ .	- \$ -	\$ -	\$	

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76548692	None					\$ -	\$ -	\$ -
					Total	\$ -	\$ -	\$ -

				Earliest Start	Redispatch
Reservation	Upgrade Name	DUN	EOC	Date	Available
76548692	BLUE CANYON - PARADISE 138KV CKT 1	6/1/2010	6/1/2013		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	7/1/2012	7/1/2012		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
_	WOODWARD - WOODWARD EHV 138KV CKT 2	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

<sup>\*</sup>Credits may be required for applicable generation interconnection network upgrades.

Customer Study Number WFEC 2012-AG1-006

Customer	Reservation	POR			Requested Start Date	Requested Stop	Deferred Start Date Without Redispatch	Date Without	Potential Base Plan Funding Allowable		Allocated E & C	Total Revenue Requirements
WFEC	76548702		WFEC	30	6/1/2019		•	i i caispateii	\$ -	\$ -	\$	- \$ -
		•		•			•	•	\$ -	\$ -	\$	- \$ -

				Earliest Start	Redispatch	Allocated E & C		Total Revenue
Reservation	Upgrade Name	DUN	EOC	Date	Available	Cost	Total E & C Cost	Requirements
76548702	None					\$ -	\$ -	\$
					Total	\$ -	\$ -	\$

				Earliest Start	Redispatch
Reservation	n Upgrade Name	DUN	EOC	Date	Available
76	548702 BLUE CANYON - PARADISE 138KV CKT 1	6/1/2010	6/1/2013		
	CIMARRON - DRAPER LAKE 345KV CKT 1	10/1/2014	6/1/2016		
	HUGO POWER PLANT - VALLIANT 345 KV AEPW	7/1/2012	7/1/2012		
	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	7/1/2012	7/1/2012		
	HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	7/1/2012	7/1/2012		
	WOODWARD - WOODWARD EHV 138KV CKT 1	1/1/2010	1/1/2010		
	WOODWARD 345/138KV TRANSFORMER CKT 1	1/1/2010	1/1/2010		

 Table 4 - Upgrade Requirements and Solutions Needed to Provide Transmission Service for the Aggregate Study

Transmission Owner Upgrade	Solution	Earliest Date Upgrade Required (DUN)		Estimated Engineering & Construction Cost
IOKGE Hetner - Tulsa 138kV CKT 1	Reconductor 1.25 mile 138 kV Hefner - Tulsa transmission line with 1590AS52 conductor	6/1/2019	6/1/2019	\$1,131,409.00

Construction Pending Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

Transmission Owner	Upgrade	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)
OKGE	NORTHWEST 345/138/13.8KV TRANSFORMER CKT 3 Accelerated	Install third 345/138 kV Bus Tie in Northwest Sub	6/1/2014	6/1/2015
SPS	ICANYON EAST SUB - CANYON WEST SUB 115KV CKT 1	Rebuild 3.73 miles to at least 107 MVA Summer Rate B and 127 MVA Winter Rate B.	5/1/2014	6/1/2017

Expansion Plan Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

Transmission Owner	Upgrade	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)
AEPW	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1	Rebuild and reconductor 11.1-mile 161 kV line from Chamber Springs to Farmington REC with 2-959.6 ACSR/TW. Upgrade wavetraps, CT ratios, and relay settings at Chamber Springs.	6/1/2014	6/1/2015
ITCGP	Line - Clark County - Thistle 345 kV dbl Ckt	Build a new 86 mile double circuit 345 kV line with at least 3000 A capacity from the Thistle 345 kV substation to the new Clark County substation. Build a new 345 kV substation at Thistle with a ring bus and necessary terminal equipment.	5/1/2014	1/1/2015
ITCGP	Line - Spearville - Clark County 345 kV dbl Ckt	Build a new 36 mile double circuit 345 kV line with at least 3000 A capacity from the Spearville substation to the new Clark County substation. Build the Clark County 345 kV substation with a ring bus and necessary terminal equipment.	5/1/2014	1/1/2015
ITCGP	XFR - Thistle 345/138 kV	Install a 400 MVA 345/138 kV transformer at the new 345 kV Thistle substation.	5/1/2014	1/1/2015
KACP	IATAN - NASHUA 345KV CKT 1	Tap Nashua 345kV bus in Hawthorn - St. Joseph 345 kV line. Build new 345 kV line from latan to Nashua, Add Nashua 345/161 kV	6/1/2014	6/1/2015
OKGE	Line - Hitchland - Woodward 345 kV dbl Ckt OKGE	Build a new 92 mile double circuit 345 kV line with at least 3000 A capacity from the Woodward District EHV substation to the SPS interception from the Hitchland substation. Upgrade the Woodward District EHV substation with the necessary breakers and term	5/1/2014	7/1/2014
OKGE	Line - Thistle - Woodward 345 kV dbl Ckt OKGE	Build a new 79 mile double circuit 345 kV line with at least 3000 A capacity from the Woodward District EHV substation to the Kansas/Oklahoma state border towards the Thistle substation. Upgrade the Woodward Distric EHV substation with the necessary brea	5/1/2014	1/1/2015
OKGE	Line - Tuco - Woodward 345 kV line OKGE	Build new 345 kV line from Woodward EHV to Border - Project costs now include Border reactor substation	5/1/2014	6/1/2014
PW	Line - Thistle - Wichita 345 kV dbl Ckt PW	Build a new 78 mile double circuit 345 kV line with at least 3000 A capacity from the Wichita substation to the new Thistle 345 kV substation.	5/1/2014	1/1/2015
PW	Line - Thistle - Woodward 345 kV dbl Ckt PW	Build a new 30 mile double circuit 345 kV line with at least 3000 A capacity from the Thistle substation to the Kansas/Oklahoma state border towards the Woodward District EHV substation.	5/1/2014	1/1/2015
SPS	Line - Hitchland - Woodward 345 kV dbl Ckt SPS	Build 30 mile double circuit 345 kV line with at least 3000 A capacity from the Hitchland substation to the OGE interception point from the Woodward District EHV substation. Upgrade the Hitchland substation with the necessary breakers and terminal equipme	5/1/2014	7/1/2014
SPS	Line - Tuco - Woodward 345 kV line SPS	Build new 345 kV line from Tuco to OGE Border station near TX/OK Stateline. Install line reactor outside Border station and line reactors at Tuco.	5/1/2014	6/1/2014
WERE	Line - Thistle - Wichita 345 kV dbl Ckt WERE	Upgrade the Wichita substation with the necessary breakers and terminal equipment to accommodate two new 345 kV circuits from the new Thistle 345 kV substation		1/1/2015

Reliability Projects - The requested service is contingent upon completion of the following upgrades. Cost is not assignable to the transmission customer.

Transmission Owner	Upgrade	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)
MKEC	CIMARRON RIVER TAP - KISMET 3 115.00 115KV CKT 1	Rebuild 3.37 miles and Substation work	10/1/2018	10/1/2018
MKEC	CUDAHY - KISMET 3 115.00 115KV CKT 1	Rebuild 23.17 miles and increase terminal limits to at least 146MVA Summer Rate B.	10/1/2018	10/1/2018
OKGE	DIVISION AVE - LAKESIDE 138KV CKT 1	Rebuild 3.58 mile line with 1590AS52 Conductor	6/1/2019	6/1/2019
SPS	BUSHLAND INTERCHANGE - DEAF SMITH COUNTY INTERCHANGE 230KV CKT 1	Upgrade 800A wave trap at both Bushland Interchange and Deaf Smith Interchange to at least 428 MVA Winter Rate B. Deaf Smith - Replace existing wave trap so that the limiting factor of K-11 terminal at Deaf Smith will be no less than 1200 A.	10/1/2014	6/1/2016
SPS	CANYON EAST SUB - RANDALL COUNTY INTERCHANGE 115KV CKT 1	Rebuild 18 miles to at least 107 MVA Summer Rate B and 127 MVA Winter Rate B.	6/1/2014	6/1/2017
WERE	Butler - Weaver 138kV CKT 1 #2	Rebuild the 138kV Butler to Weaver line with new poles, conductor, and shield wire. Upgrade relays at both ends to achieve 1200 amp rating.	6/1/2015	6/1/2018
WERE	Cowskin - Westlink 69 kV Ckt 1	Rebuild 2.1-mile 69 kV line from Cowskin to Westlink.	6/1/2014	12/1/2015
WERE	East Manhattan - Jeffrey Energy Center 230 kV Ckt 1	Rebuild 27-mile 230 kV line from East Manhattan to Jeffrey Energy Center to 345 kV construction but operate as 230 kV using bundled 1590 ACSR conductor. Upgrade terminal equipment at East Manhattan and Jeffrey Energy Center to a minimum emergency rating o	6/1/2019	6/1/2019
WERE	Gill 138/69 kV Transformer Ckt 3	Install a third 138/69 kV transformer at Gill Energy Center.	6/1/2014	12/1/2015
WERE	Hoover South - Tyler 69 kV Ckt 1	Rebuild 1.96-mile 69 kV line from Tyler to Hoover.	6/1/2014	6/1/2014
WERE	Tyler - Westlink 69 kV Ckt 1	Rebuild 2.65-mile 69 kV line from Westlink to Tyler. Install terminal equipment at Tyler.	6/1/2014	6/1/2015
WERE	Viola - Clearwater 138kV Ckt1	Build new 138kV line between new Viola substation 345/138 kV transformer and existing Clearwater 138 kV substation.	10/1/2014	6/1/2018
WERE	Viola - Gill 138kV Ckt1	Build new 138kV line between new Viola substation 345/138 kV transformer and existing Gill 138 kV substation.	10/1/2014	6/1/2018
WERE	Viola 345/138kV Transformer Ckt 1	Install new 345/138 kV transformer at Viola substation	10/1/2014	6/1/2018

Transmission Owner	Upgra	le Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)
AEPW	ASHDOWN REC (MILLWOOD) - OKAY 138KV CKT 1	Recunductor and convert line to 138 kV and replace switches at Ashdow REC	7/1/2012	7/1/2012
AEPW	ASHDOWN REC (MILLWOOD) - PATTERSON 138KV CKT 1	Reconductor Line & Convert Line to 138 kV and convert Patterson station to breaker-and-a half cofiguration	7/1/2012	7/1/2012
AEPW	BANN - RED SPRINGS REC 138KV CKT 1	Replace 138 kV breakers 3300 & 3310	7/1/2012	7/1/2012
AEPW	HUGO POWER PLANT - VALLIANT 345 KV AEPW	Vallient 345 KV line terminal	7/1/2012	7/1/2012
AEPW	MANDEVILTP4 - SE TEXARKANA 138KV CKT 1	Build new Turk-SE Texarkana 138 kV line and add SE Texarkana 138 kV terminal.	7/1/2012	7/1/2012
AEPW	MANDEVILTP4 - TURK 138KV CKT 1	Build new Turk-SE Texarkana 138 kV line and add SE Texarkana 138 kV terminal.	7/1/2012	7/1/2012
AEPW	MCNAB REC - TURK 115KV CKT 1	Build a new two mile, 138 kV, 1590 ACSR line section (operated at 115 kV from Turk Substation to the existing Okay- Hope 115 kV line to form a Turk - Hope 115 kV line.	7/1/2012	7/1/2012
AEPW	OKAY - TURK 138KV CKT 1	Build two mile, 138 kV, 1590ACSR line section from Turk Sub to existing Okay-Hope 115 kV line and rebuild twelve miles of 115 kV line to Okay Sto 138 kV, 1590 ACSR, to form a Turk-Okay 138 kV line	ub 7/1/2012	7/1/2012
AEPW	SUGAR HILL - TURK 138KV CKT 1	Build new Turk-Sugar Hill 138 kV line and add Sugar Hill 138 kV terminal.	7/1/2012	7/1/2012
EMDE	SUB 110 - ORONOGO JCT SUB 167 - RIVERTON 161KV CKT 1	Reconductor Oronogo 59467 to Riverton 59469 with Bundled 556 ACSR	6/1/2011	6/1/2011
KACP	LACYGNE - WEST GARDNER 345KV CKT 1	KCPL Sponsored Project to Reconductor Line to be In-Service by 6/1/200	6 6/1/2006	6/1/2006
MIDW	CIRCLE - RICE_CO 230KV CKT 1	Convert from 115kV to 230kV operation	10/1/2012	11/15/2012
MIDW	LYONS - RICE_CO 115KV CKT 1	Rebuild 11.7 mile line	10/1/2012	4/1/2013
MIDW	RICE_CO 230/115KV TRANSFORMER CKT 1	Add 230/115kV Transformer	10/1/2012	11/15/2012
MKEC	ALEXANDER - PRATT 115KV CKT 1	Rebuild line	12/1/2009	6/1/2013
MKEC	BARBER - MEDICINE LODGE 115KV CKT 1	Rebuild line	12/1/2009	6/1/2013
MKEC	BARBER - SAWYER 115KV CKT 1	Rebuild line	12/1/2009	6/1/2013
MKEC	BARBER (BARBER 4) 138/115/2.72KV TRANSFORMER CKT 1	Upgrade transformer	12/1/2009	6/1/2013
MKEC	CLIFTON - GREENLEAF 115KV CKT 1	Rebuild 14.4 miles	6/1/2011	6/1/2013
MKEC	FLATRDG3 138.00 - MEDICINE LODGE 138KV CKT 1	Rebuild 8.05 mile line	12/1/2009	6/1/2013
MKEC	FLATRDG3 138.00 - HARPER 138KV CKT 1	Rebuild 24.15 mile line	12/1/2009	6/1/2013
MKEC	GREENLEAF - KNOB HILL 115KV CKT 1 MKEC	Rebuild 43.5% Ownership of 20.9 miles	6/1/2013	6/1/2013
NPPD	ALBION - PETERSBURG 115KV CKT 1	Replace Breaker Switch 1106-D and jumpers at Albion. Replace main bus at Petersburg. Upgrade and replace transmission structures on 115 kV lineto facilitate 100 degrees Centigrade line operation.	1/1/2013	1/1/2013
NPPD	NELIGH - PETERSBURG 115KV CKT 1	Replace Breaker 1106, jumpers, and 115 kV Switch 1106-D2 at Neligh.  Replace main bus at Petersburg. Upgrade and replace transmission structures on 115 kV lineto facilitate 100 degrees Centigrade line operation.	1/1/2013	1/1/2013
OKGE	CIMARRON - DRAPER LAKE 345KV CKT 1	Increase capacity of Draper Lake CT and Cimarron wave trap	10/1/2014	6/1/2016
OKGE	GRACMNT4 138.00 - WASHITA 138KV CKT 2 OKGE	Build 138kV Terminal.	1/1/2012	1/1/2012
OKGE	NORTHWEST - TATONGA 345KV CKT 1	Build 345 kV line	1/1/2010	1/1/2010
OKGE	TATONGA - WOODWARD 345KV CKT 1	Build 345 kV line	1/1/2010	1/1/2010
OKGE	WOODWARD - IODINE 138KV CKT 1	Tap Iodine to Woodward 138 kV line	1/1/2010	1/1/2010
OKGE	WOODWARD - WOODWARD EHV 138KV CKT 1	Build .5 miles of 138 kV and install terminal equipment	1/1/2010	1/1/2010
OKGE	WOODWARD - WOODWARD EHV 138KV CKT 2	Build .5 miles of 138 kV and install terminal equipment	1/1/2010	1/1/2010
OKGE	WOODWARD 345/138KV TRANSFORMER CKT 1	Install 345/138 kV XF	1/1/2010	1/1/2010
SPS	CHERRY6 230.00 - Harrington Station East Bus 230KV CKT 1	Replace wavetrap at Harrington East	6/1/2015	6/1/2015
WERE	DEARING 138KV Capacitor	Dearing 138 kV 20 MVAR Capacitor Addition	6/1/2012	6/1/2012
WERE	LYONS - WHEATLAND 115KV CKT 1 #1	Replace CTs	10/1/2012	7/15/2013
WERE	LYONS - WHEATLAND 115KV CKT 1 #2	Rerate circuit to 1000 amps	10/1/2012	7/15/2013
WFEC	BLUE CANYON - PARADISE 138KV CKT 1	Upgrade Paradise to Blue Canyon to 1113	6/1/2010	6/1/2013
WFEC	GRACMNT4 138.00 - WASHITA 138KV CKT 2 WFEC	Build approximately 6 miles of 138kV.	1/1/2012	1/1/2012
WFEC	HUGO POWER PLANT - VALLIANT 345KV CKT 1 WFEC	New 19 miles 345 KV	7/1/2012	7/1/2012
WFEC	HUGO POWER PLANT 345/138KV TRANSFORMER CKT 1	New 345/138 kv Auto	7/1/2012	7/1/2012

## Table 5 - Third Party Facility Constraints

Transmission Owner	UpgradeName	Solution	Earliest Date Upgrade Required (DUN)	Estimated Date of Upgrade Completion (EOC)	Estimated Engineering Construction	g &
		Upgrade 1272 AAC bus at Farmington REC. Replace bus at Farmington REC				
AECC	CHAMBER SPRINGS - FARMINGTON AECC 161KV CKT 1 AECC	and rebuild 400 feet of the 161 kV line going to Chamber Springs.	6/1/2018	6/1/2019	\$	26,061